

Wind turbine rotors in surge motion: New insights into unsteady aerodynamics of FOWT from experiments and simulations

Christian W. Schulz¹, Stefan Netzband¹, Umut Özinan², Po Wen Cheng², and Moustafa Abdel-Maksoud¹

¹Hamburg University of Technology, Am Schwarzenberg-Campus 4, 21073 Hamburg, Germany

²Stuttgart Wind Energy at University of Stuttgart, Allmandring 5b, 70569 Stuttgart, Germany

Correspondence: Christian W. Schulz (christian.schulz@tuhh.de)

Abstract. An accurate prediction of the unsteady loads acting on floating offshore wind turbines (FOWT) under consideration of wave excitation is crucial for a resource-efficient turbine design. Despite a considerable number of simulation studies in this area, it is still not fully understood, which unsteady aerodynamic phenomena have a notable influence on the loads acting on a wind turbine rotor in motion. In the present study, investigations are carried out to evaluate ~~of~~ the most relevant unsteady aerodynamic phenomena for a wind turbine rotor in surge motion. As a result, inflow conditions are determined for which a significant influence of these phenomena on the rotor loads can be expected.

The experimental and numerical investigations are conducted on a two-bladed wind turbine rotor subjected to a tower top surge motion. A specialised wind tunnel test rig has been developed to measure the aerodynamic torque response of the rotor subjected to surge motions with moderate frequencies. The torque measurements are compared to two free vortex wake methods, namely a panel and a ~~lifting-line~~ lifting line method. Unsteady contributions that cannot be captured using quasi-steady modelling have not been detected in either the measurements or the simulations in the covered region of ~~motion frequencies~~ motions ranging from a rotor reduced frequency of 0.55 to 1.09 and motion velocity amplitudes up to 9% of the wind speed. The surge motion frequencies were limited to a moderate range (5 to 10 Hz) due to vibrations occurring in the experiments. Therefore, a numerical study with an extended ~~the~~ range of motion frequencies using the panel and the ~~lifting-line~~ lifting line method was performed. The results from both FVW methods reveal significant unsteady contributions of the surge motions to the torque and thrust response that ~~cannot be modelled in a quasi-steady way~~ have not been reported in recent literature. Furthermore, the results show the presence of the returning wake effect, which is known from helicopter aerodynamics. Additional simulations of the UNAFLOW scale model and the IEA 15 MW rotor demonstrate that the occurrence of the returning wake effect is independent from the turbine, but determined by the ratio of ~~rotor speed-3P~~ and surge motion frequency. In case of the IEA 15 MW, a notable impact of the returning wake effect was found at surge motion frequencies in the range of typical wave periods. Finally, a comparison with OpenFAST simulations reveals notable differences in the modelling of the unsteady aerodynamic behaviour in comparison to ~~a FVW method~~ the FVW methods.

1 Introduction

The rapid development of floating offshore wind turbines has been enabled by elaborate simulation techniques that are improving continuously with the needs of new wind turbine designs. In case of new, large scale FOWT, the reliability of these simulation methods becomes more and more crucial for the evaluation of their feasibility and safety. In order to assess whether a numerical method is sufficiently reliable for such FOWT concepts, the underlying physical phenomena must be understood and characterised. Due to increasing rotor diameters, the relevance of various aerodynamic phenomena to wind turbine rotor loads must be continuously re-evaluated. Therefore, many current research activities in the field of floating wind turbine aerodynamics focus on the occurrence and effects of unsteady aerodynamic phenomena caused by the motions of the tower top of large wind turbines. Although a considerable number of studies have been carried out on this subject, no consensus has been reached in the research community on which unsteady aerodynamic phenomena are relevant and how much they can influence the loads acting on the wind turbine. Accordingly, the present work is intended to contribute to the understanding and characterisation of such unsteady phenomena and their influence on the loads of FOWT rotors using a novel experimental approach and comprehensive numerical investigations.

In the first step, an experimental study on a model rotor subjected to a surge motion is presented and load measurements are compared to simulations using two different free vortex wake (FVW) methods. A-It is shown that both FVW methods perform well, but have slightly different qualities in the context of modelling unsteady phenomena. On the experimental side, a special test rig was developed for the experimental investigation to minimise vibrations and an elaborate data acquisition procedure was applied to gain reliable and precise measurement results at high surge motion frequencies.

In the second step, the results of further numerical simulations exceeding the physical limits of the test rig are presented. A specialised set of load cases is used to clearly differentiate between quasi-steady and unsteady aerodynamic phenomena impacting the simulation results. Apart from the well-known unsteady airfoil effect and the dynamic inflow effect, the simulations show a significant impact of the returning wake effect on the loads of the surging model rotor. This effect is known from helicopter aerodynamics, but has received very little attention in the context of FOWT to date. In order to investigate the relevance of the returning wake effect for different turbines, the analysis ~~was extended to the rotor~~ is extended to another model rotor and a representative for modern full-scale Offshore Wind Turbines. The rotor used in the UNAFLOW (Fontanella et al., 2021) measurement campaign and the large scale IEA was chosen, because it was subject of the recently finished IEA Task 30 (OC 6¹, see (Bergua et al., 2023)), which also aimed at identifying unsteady aerodynamic effects caused by surge motions. For the sake of easy reproduction of the results, the IEA 15 MW wind turbine (Gaertner et al., 2020)-

turbine (Gaertner et al., 2020) was chosen as a full-scale representative. The extension of the simulation study to the IEA 15 MW turbine allows a transfer of the findings from the model rotors and reveals the presence of significant unsteady contributions to the load response at small wave periods. Finally, a comparison of the free vortex wake simulation results of the IEA 15 MW turbine and those obtained by AeroDyn/OpenFAST (Jonkman, 2022) provides insight into the capabilities

¹Offshore Code Comparison, Collaboration, Continued, with Correlation and uncertainty

55 and limitations of a state-of-the-art blade element momentum theory (BEMT) method in the context of ~~a surging wind turbine rotor and the returning wake effect~~ unsteady aerodynamics caused by surge motions.

The present work is structured as follows. Sections 2 and 3 ~~briefly~~ summarise the theory and current state of research regarding moving and especially surging wind turbine rotors ~~;-The panel method panMARE and its lifting-line module as well as the simulation setups are and the corresponding unsteady aerodynamic phenomena. The utilised numerical models are briefly~~ described in section 4. A summary of the experimental setup, the test rig and the data acquisition followed by a comparison of experimental and numerical results is given in section 5, ~~while the simulation studies on the three rotors are presented in sections 6 and ??~~. In the subsequent section ~~;-the characterisation and scaling~~ 6, the range of motions is extended in a purely numerical study of the TUHH model rotor. The transferability of the findings from the TUHH model rotor to the UNAFLOW and the IEA 15 MW rotor is investigated in sections 7.1 and 8. A characterisation of the observed unsteady phenomena and 65 their impact on the rotor loads ~~using dimensionless numbers are discussed based on dimensionless numbers is discussed in section 9~~. Finally, the main results of the experimental and numerical investigations are summarised in section 10.

2 Theoretical background

2.1 Quasi-steady and ~~transient~~ unsteady parts of a rotor's load response to a surge motion

The load response of a wind turbine rotor to a tower top surge motion is generally unsteady as the surge motion velocity 70 varies the inflow conditions over time. However, in case of a very slow motion, this ~~unsteady~~ response can be described in a *quasi-steady* way. Considering a very fast motion, it is likely that the behaviour of the rotor loads will be affected by additional aerodynamic phenomena ~~;-caused e.g. by vortex shedding~~. Such behaviour is referred to as ~~transient~~ unsteady in this work, ~~because the frequently used term unsteady may lead to confusion as it also includes~~ which does not include any quasi-steady ~~behaviour~~ effects.

75 As a consequence, the aerodynamic power of a wind turbine in motion can be divided into a quasi-steady and ~~a transient an~~ unsteady part. For a harmonic surge motion with a velocity $v_m(t)$ and velocity amplitude V_m at constant rotational speed and constant wind speed, these parts can be described as follows:

$$\underline{P}v_m(t) = \underline{\text{quasi-steady}} + \underline{\text{transient}}, \underline{V_m \sin(2\pi ft)} \quad (1)$$

$$80 \quad P(t) = \underbrace{\frac{\rho AC_p(\lambda(t))}{2} (v_0 + V_m \sin(2\pi ft))^3}_{\text{quasi-steady}} + \underbrace{P_{\text{unsteady}}(t)}_{\text{unsteady}} \quad (2)$$

where P , C_p , λ and f describe the aerodynamic power, power coefficient, tip speed ratio and motion frequency of the wind turbine. ρ and v_0 denote air density and wind speed, respectively. It has to be noted, that λ can be determined by the time dependent motion velocity in this case. All potential ~~transient~~ unsteady influences on the ~~unsteady~~ power are summarised in ~~P_{trans}~~ P_{unsteady} .

85 Introducing the dimensionless number b_{vel} as the ratio of *motion to inflow velocity*, the power amplitude can be expressed as:

$$b_{vel} = \frac{V_m}{v_0} \quad (3)$$

$$P_{amp} = \underbrace{\frac{\rho A v_0^3}{2} \frac{1}{2} \left(C_p(\lambda_{min})(1 + b_{vel})^3 - C_p(\lambda_{max})(1 - b_{vel})^3 \right)}_{\text{quasi-steady}} + \underbrace{\text{transient} \Delta P_{\text{unsteady}}}_{\text{unsteady}} \quad (4)$$

A detailed derivation of equation (4) and the following equations is given in appendix A. The same derivation is valid for
90 the rotor torque at constant rotational speed. Similarly, the thrust T_{amp} amplitude can be expressed as:

$$T_{amp} = \underbrace{\frac{\rho A v_0^2}{2} \frac{1}{2} \left(C_t(\lambda_{min})(1 + b_{vel})^2 - C_t(\lambda_{max})(1 - b_{vel})^2 \right)}_{\text{quasi-steady}} + \underbrace{\text{transient} \Delta T_{\text{unsteady}}}_{\text{unsteady}}, \quad (5)$$

where C_t describes the thrust coefficient. It has to be noted that λ_{min} and λ_{max} are also determined by b_{vel} . This is due to the assumption of constant rotational speed and wind speed. Therefore, it can be concluded that the quasi-steady part of the power amplitude as a response of a harmonic surge motion is exclusively dependent on the dimensionless number b_{vel} . This
95 knowledge will be used in section 6 to derive a set of load cases, which is suitable to distinguish the quasi-steady part of the load response from the ~~transient~~unsteady part.

2.2 ~~Transient~~Unsteady aerodynamic phenomena

Leishman (2002) describes three ~~transient~~unsteady aerodynamic phenomena that were found to be most significant in the context of wind turbine rotors. Namely, the *unsteady airfoil* effect (attached flow), the *dynamic inflow* effect and *dynamic stall*.
100 This is in line with Schepers' selection of relevant ~~transient~~unsteady aerodynamic phenomena (Schepers, 2012). In addition to that, Eliassen (2015) showed that the *returning wake* effect may also influence the aerodynamic loads acting on a wind turbine in case of tower top vibrations. For the sake of simplicity, the experimental and numerical setups in the present work are designed so that stall has no or minor influence on the rotor loads. As a consequence, only the other three effects are described briefly in the following, while details can be found in the above mentioned publications.

105 **Unsteady airfoil effect**

The unsteady airfoil effect for attached flow describes two physical phenomena that are referred to as *circulatory* and *non-circulatory*. The circulatory effect is based on the fact that vortices are shed from the trailing edge of an airfoil when its circulation (i.e. lift force) changes. In turn, these vortices influence the angle of attack of the airfoil, which results in a mutual interaction between the angle of attack and the change of the lift force. This is a consequence of Kelvin's theorem, which claims
110 that the ~~emulated~~accumulated circulation in a closed fluid volume cannot change. The shed vortices are then transported

downstream, which causes their influence on the angle of attack to vanish over time. The non-circulatory effect refers to added mass forces that act on the airfoil surface, which are caused by an acceleration or deceleration of the flow field around the airfoil. Such forces may occur e.g. when the airfoil is pitching or plunging. In case of a sinusoidal variation of the angle of attack in a frequency range that can be expected in the context of wind turbines, the circulatory effect is most prominent. It causes a time lag and a decrease of the lift amplitude with increasing frequency.

A reduced frequency f_a was described by Sebastian and Lackner (2013) to characterise the influence of the unsteady airfoil effect on a wind turbine blade section:

$$f_a = \frac{\pi f c(r)}{\sqrt{v_0^2 + (r\Omega)^2}}. \quad (6)$$

Here, v_0 and Ω describe the wind velocity and the angular speed of the rotor while r and c are the radius and chord length of the radial section under investigation, respectively. f denotes the frequency with which the inflow conditions vary (i.e. surge motion frequency). f_a is referred to as the *airfoil reduced frequency* in this work.

Leishman proposed that the flow around an airfoil may be considered as quasi-steady up to $f_a = 0.05$ (Leishman, 2000). As the airfoil reduced frequency varies strongly over the blade span, it is difficult to use the value of f_a as a clear indicator for the strength of unsteady airfoil effect acting on the whole rotor.

125 **Dynamic inflow effect**

The helical vortex structure in the wake of a wind turbine induces an axial velocity component at the rotor plane, which is referred to as the induction. This induction has significant influence of the angle of attack at the blade sections and consequently on the rotor loads. A change of the inflow situation of the rotor (i.e. due to a blade pitch event) leads to an adaptation of the wake structure and vortex strength, which in turn causes a change of the induction of the rotor. As the wake is transported downstream, the induction is influenced by the newly shed vortices as well as the 'old' wake structure. The influence of the 'old' wake decays over time until a new steady state of the wake and induction is reached. Consequently, the induction of the rotor can only change gradually after a change of the inflow, which is the main impact of the dynamic inflow effect.

In the context of a surge motion, the dynamic wake effect can be characterised by a normalised 'advection wave length' introduced by Sebastian and Lackner (2012). A more convenient way is to utilise its inverse, which known as *wake or rotor reduced frequency* f_r :

$$f_r = \frac{fD}{v_0} \quad (7)$$

where D denotes the rotor diameter. Typical values for the rotor reduced frequency corresponding to wave induced motions may reach up to 8^2 .

²A rotor reduced frequency of 8 approximately corresponds to a 20 MW turbine at 5 m s^{-1} wind speed and a wave induced motion period of 7 s.




Figure 1. Schematic sketch of the vortex shedding at four steps during a surge motion cycle in the two-dimensional projection. The actual surge motion position varies between x_{min} (turbine moved in wind direction) and x_{max} (turbine moved against-against wind direction). Dashed, grey arrows illustrate the motion-motion velocity. Full, black arrows indicate the local flow direction induced by the vortices. The green line represents the strength of the shed vorticity, which varies in a sinusoidal manner.

Returning wake effect

140 As already mentioned in the context of the unsteady airfoil effect, vortices are shed from the trailing edge of an airfoil when the circulation around it changes rapidly. In case of a rotor, these vortices may not only have an influence on the blade that was shedding them, but can also affect the flow situation around the following blades passing the same azimuth angle. In case of an oscillatory excitation of the inflow, the returning wake effect leads to a significant decrease of the load amplitude when the frequency of the vortex shedding matches the blade frequency.

145 This effect can be illustrated when considering the influence of the shed vortices of an airfoil on the flow field of a second
airfoil behind it. In Figure 1, the history of the shed vortices during a cycle of a periodic surge motion ³ of two airfoils in a
row is illustrated schematically. In the presented case, the period of the motion is assumed to be equal to the time a vortex shed
from the first airfoil needs to be transported to the second airfoil. The four rows shown in the figure correspond to four different
positions during the surge motion. The first row represents the zero crossing of the surge motion during the downwards motion.
150 In the second row, the maximum position is reached, while the third and fourth correspond to the zero crossing in upward
direction and the minimum position respectively. During the downward motion, the presence of the motion velocity leads to an
increase of the the angle of attack and finally to a maximum of the lift force. The opposite is the case during the upward motion.
The strength of the shed vortices is determined by the rate of change of the angle of attack, which is correlated to the actual
rate of change of the surge motion velocity. In case of the downward motion in the first row, the motion velocity is maximum,
155 which results in a zero rate of change of the angle of attack and no vortex shedding. When the airfoil reaches the maximum
position in the second row, the rate of change of the angle of attack is negative. Therefore, clockwise vortices are shed from
the trailing edge of the airfoil. In the third row, where the zero position is reached during the upward motion, the rate of change
of the angle of attack and the vortex shedding is zero again. Finally, the shedding of ~~counterclockwise~~ anticlockwise vortices
in the fourth row is caused by the positive rate of change of the angle of attack at the minimum position. This procedure is the
160 same in every surge motion period, which results in an alternating shedding of clockwise and ~~counterclockwise~~ anticlockwise
vortices with the motion frequency.

The lift amplitude of both airfoils oscillate due to the surge motion. In the example, the vortices shed in one time instant reach
the second airfoil exactly after one surge motion period. The superposition of the flow fields of the vortices yield an alternating
upwards and downwards flow. In case these flow regimes are near the second airfoil, its angle of attack is deviated ~~by them. In~~
165 ~~the first row, the vortex induced velocity leads to a decrease of the angle of attack, when the airfoil has its maximum downward~~
~~motion velocity. Concurrently, the lift force is maximum due the downward motion motion of the airfoils. Therefore, the vortex~~
~~induced velocity causes a decrease of the maximum lift force of the second airfoil. The opposite is the case in the third row,~~
~~where the vortex induced velocity increases the angle of attack during the upward motion. As the minimum lift force occurs~~
~~during the upward motion, this minimum increases due to the presence of the shed vortices. Consequently, the lift amplitude of~~
170 ~~the second airfoil caused by the surge motion decreases due to the presence of the shed vortices in case the vortices reach the~~
~~second airfoil after one motion period. In a similar way, it can be argued that a maximum of the lift force occurs when vortices~~
~~reach the second airfoil after half a motion period. so that the amplitude of the lift force due to the surge motion is decreased~~⁴

³In the reference frame of the airfoil the surge motion of the rotor would be a plunge motion. However, for the sake of simplicity, the term surge motion is used here.

⁴In the first row of Figure 1, the vortex induced velocity leads to a decrease of the angle of attack, when the airfoil has its maximum downward motion velocity. Concurrently, the lift force is maximum due the downward motion motion of the airfoils. Therefore, the vortex induced velocity causes a decrease of the maximum lift force of the second airfoil. The opposite is the case in the third row, where the vortex induced velocity increases the angle of attack during the upward motion. As the minimum lift force occurs during the upward motion, this minimum increases due to the presence of the shed vortices. Consequently, the lift amplitude of the second airfoil caused by the surge motion decreases due to the presence of the shed vortices in case the vortices reach the second airfoil after one motion period. In a similar way, it can be argued that a maximum of the lift force occurs when vortices reach the second airfoil after half a motion period.




Figure 2. Illustration of blades and wake of the TUHH rotor as modelled in the panel method. A sectional view of blades and wake at a relative radius of 62% is shown in black.




Figure 3. Illustration of a cylindrical cut at 62% of the rotor radius through the blades and wake. The projection of the blades and wake on the cylinder at this radius is indicated in black.

175 The illustrated situation in Figure 1 can be adopted to a wind turbine rotor in surge motion. In this case, the two airfoils represent the blade sections of the wind turbine blades at the same radial position (see Figure 2). The airfoils in the two-dimensional case represent a cylindrical cut through the blades at a certain radius as indicated in Figures 2 and 13. When unrolling this cylindrical cut through the blades and the wake, a situation comparable to the one in 1 results. The distance between the airfoils is assumed to be equal to the distance one blade section travels until the next blade passes in the three-dimensional case. Therefore, the time until the second blade passes the position where the vortices were emitted from the first blade is equal to

1/2 of the rotation period of the rotor (for a two-bladed rotor). As a consequence, the above described drop of the lift amplitude
180 occurs, when the motion period equals 1/2 of the rotation period.

This effect is known as returning wake effect from helicopter aerodynamics (Leishman, 2000) and was described mathematically by Loewy (1957). It can be described by the ratio of both frequencies:

$$q_b = \frac{2\pi f}{n_b \Omega}, \quad (8)$$

where n_b and Ω denote the number of blades and the angular velocity of the rotor respectively. In case of a harmonic surge
185 motion of a wind turbine, this means that a drop of the lift amplitude of the blades occurs when the motion frequency is equal to or a multiple of the blade passing frequency. q_b would be an integer in this case.

In addition, the influence of the shed vortices on the lift force of the following blade is dependent on the distance from the blade to the vortices emitted by the preceding blade. A more detailed explanation of the physical principle is given in Eliassen (2015).

190 Influence of unsteady phenomena on torque and thrust

The above mentioned phenomena primarily affect the lift force of the rotor blades. While the returning wake effect and the unsteady airfoil effect can be considered as a perturbation of the local angle of attack, the dynamic inflow effect affects the axial induction. Both, a perturbation of the angle of attack and a change of the axial induction, affect rotor torque and thrust simultaneously. Therefore, the general characterisation of these unsteady phenomena on rotor level can be performed either on
195 the basis of rotor torque or thrust.

2.3 Suitability of FVW methods for wind turbine aerodynamics

Lifting line FVW methods have ~~proofed~~ proven their ability to predict the loads acting wind turbine rotors under typical, stationary operation conditions in several comparisons with experimental studies, see Schepers (2012) for example. The same is true for FVW panel methods (van Garrel, 2016; Roura et al., 2010), except for the occurrence of stalled blades. However, it
200 is more challenging to incorporate the influence of viscous effects on the blade loads into panel methods than into lifting line methods. The reason is that the flow around the airfoil is explicitly modelled and cannot be altered in a simple manner while the lifting line algorithm disregards the local flow field and fully relies on empirical lift and drag coefficients. As a consequence, despite their higher modelling fidelity panel methods are often a little less reliable in predicting wind turbine loads in steady conditions. FVW methods are ~~also~~ generally capable of modelling the circulatory unsteady airfoil effect. This is due to the fact
205 that the vortices emitted into the wake due to a change of circulation around the airfoil are directly modelled in these methods. However, the non-circulatory part caused by the accelerated fluid around the airfoil can only be modelled directly by unsteady FVW panel methods representing the whole blade surface instead of a single lifting line. This effect can be introduced in lifting line methods by means of empirical corrections. The dynamic inflow effect and the returning wake effect are caused by a varying strength and motion trajectory of the vortices in the wake due to unsteady changes of the circulation around the
210 blades and/or the inflow conditions. This is directly modelled in FVW methods, which means that both effects can be captured

by these methods. In [praetisepractice](#), the ability of a lifting line method to explicitly model the dynamic inflow effect has also been shown in the past, e.g. by Schepers (2012) in conjunction with a pitch step of the NREL Phase VI experiment. As there is no fundamental difference in the wake treatment between lifting line and panel methods, this can also be transferred to panel methods.

215 3 Previous numerical and experimental works

3.1 Numerical investigations

A large number of simulation studies on the aerodynamic behaviour of wind turbine rotors undergoing typical FOWT motions have been presented in recent literature. A selection of these studies is listed in table 1. While a wide range of motion conditions is covered, the variety of wind turbine models is fairly limited among the listed studies. ~~Most frequently, the NREL 5 MW turbine (Jonkman et al., 2009) with a rotor diameter of 126 m is considered, which is a comparably small size from today's perspective. Recently, the rotor utilised in the UNAFLOW test campaign is considered more frequently.~~

The characterisation of the aerodynamic load response to a rotor motion and the influence of [transient unsteady](#) phenomena is addressed in most of the listed studies. Often, a harmonic tower top surge motion is chosen in order to simplify the analysis of the simulation results. Among these, some studies utilising FVW or RANS methods report a linear increase of the normalised thrust force amplitude with the motion frequency or motion to inflow velocity ratio b_{vel} (see equation (3)). Wen et al. (2017) and Sant et al. (2015) found that the thrust force amplitude is linearly dependent on b_{vel} , as long as the b_{vel} stays in a moderate range below approximately 15 %. This can be explained by assuming a constant C_t and neglecting the higher order terms in equation (5) (and (A6)). However, these assumptions are only valid for moderate b_{vel} and the absolute limits are dependent on the special case. In the FVW and RANS simulations of Mancini et al. (2020) and Ribeiro et al. (2023), a linear rise of the thrust amplitude ΔT , which is normalised by the motion amplitude A , with the motion frequency is present. This can be expressed as:

$$\frac{\Delta T}{A} \propto f. \quad (9)$$

When considering that the motion to inflow velocity ratio is proportional to the product of motion frequency and amplitude,

$$b_{vel} \propto fA \quad (10)$$

235 it can be easily shown that this is equivalent to the above mentioned linear relation between the thrust amplitude and b_{vel} .

$$\Delta T \propto b_{vel} \quad (11)$$

In consequence, a constant motion to inflow velocity ratio results in an approximately constant power and thrust amplitude which is confirmed by Wen et al. (2017). In the above mentioned cases, the thrust response amplitude can therefore be described in a quasi-steady way so that ~~a transient an unsteady~~ contribution is most likely not present in a moderate range of b_{vel} . This

Table 1. Selection of numerical investigations on rotor loads of surging and pitching wind turbines based on mid and high fidelity simulation approaches.

Authors	Methods	Turbine	Motions	Rotor reduced frequency* [-]	Motion to inflow velocity ratio* [%]	Norm. surge amplitude* [%]
Sebastian et al. (2012)	FVW, BEMT	NREL 5 MW	surge + pitch			
De Vaal et al. (2014)	AD, BEMT	NREL 5 MW	surge	0.23 - 0.90	4 - 71	3 - 13
Micallef et al. (2015)	AD, BEMT, GDW	NREL 5 MW	surge	1.23	6	0.8
Tran et al. (2015)	CFD, BEMT, GDW	NREL 5 MW	surge	0.23 - 1.35	4.5 - 108	3 - 13
Tran et al. (2015)	CFD, BEMT, GDW	NREL 5 MW	pitch	0.38 - 2.29		
Farrugia et al. (2015)	FVW, BEMT	NREL 5 MW	surge	0.83 - 2.21	5 - 15	1.1
Sant et al. (2015)	FVW, BEMT	scale model	surge	0.36 - 0.83		
Sant et al. (2016)	FVW, BEMT, GDW	NREL 5 MW	surge + pitch			
Wen et al. (2017)	FVW	NREL 5 MW	surge	0.55 - 5.53	- 41	
Wu et al. (2017)	FVW, CFD, GDW	NREL 5 MW	pitch	1.97 - 15.75		
Cormier et al. (2018)	FVW, CFD, BEMT	UNAFLOW	surge	0.60 - 1.19	2 - 6	- 1.5
Lienard et al. (2020)	CFD	NREL 5 MW	surge, pitch	1.11	44 - 88	6 - 13
Fang et al. (2020)	CFD	scale model	pitch	0.52 - 4.18		
Mancini et al (2020)	CFD, FVW, BEMT	UNAFLOW	surge	0.07 - 1.19	2 - 5	- 5
Chen et al. (2021)	CFD	NREL 5 MW	pitch + yaw			
Ferreira et al. (2022)	CFD, Semi-FVW, BEMT	NREL 5 MW	surge	0.16 - 3.19	10 - 200	10
Mancini et al. (2022)	FVW, BEMT	UNAFLOW	pitch	0.15		
Ribeiro et al. (2023)	FVW (panel)	UNAFLOW	surge	1.19 - 4.76	- 19	- 2
Bergua et al. (2023)	BEMT, FVW, GDW, CFD	UNAFLOW	surge	0.07 - 1.19	2 - 5	- 5
Schulz et al. (2023)	FVW (panel), BEMT	Vestas V80	surge	0.04 - 3.57	9	
Schulz et al. (present)	FVW (panel + LL), BEMT	scale model	surge	see table 3		
		UNAFLOW	surge	see table 3		
		IEA 15 MW	surge	see table 3		

* at operation conditions near optimum TSR

240 linear trend could also be confirmed during the OC6⁵ Phase III (Bergua et al., 2023). In this project, a considerable number of different low, mid and high fidelity methods were compared against each other and experiments utilising the UNAFLOW rotor. In contrast to this, lifting line FVW simulations of the NREL 5 MW wind turbine in surge motion conducted by Farrugia et al.

⁵Offshore Code Comparison, Collaboration, Continued, with Correlation and uncertainty, IEA Task 30

(2015) show a strong decrease of torque and thrust amplitudes from 0.15 Hz to 0.2 Hz at equal motion amplitudes. However, very similar simulation cases were also covered by Wen et al. (2017), who observed a linearly increasing trend again.

245 For higher motion to inflow velocity ratios (i.e. $b_{vel} > 15\%$) of the surging NREL 5 MW rotor around the design operation condition, Wen et al. found that the rise of the power amplitude becomes slightly nonlinear. A similar observation was found by Ribeiro et al. (2023) for the thrust force, where a FVW panel method was used to simulate the UNAFLOW rotor. In addition, a rising phase shift between the surge velocity and rotor thrust was reported independent from b_{vel} , which was also observed by Mancini et al. (2020) earlier. Ribeiro et al. argue that this phase shift may lead to the lower-than-expected amplitude at high
250 motion frequencies: As the strength of the unsteady airfoil effect, which most likely causes the phase shift, changes over the blade span, the phase shift also varies. Therefore, the lift contributions from the blade sections do not reach their maximum at the same time, which results in a lower ~~emulated~~accumulated amplitude. Although this reasoning seems plausible, a proof for this hypothesis is not given. However, in this case a high motion velocity was investigated concurrently with a high b_{vel} . Therefore it cannot be distinguished whether the deviation from the linear trend indicates that the quasi-steady part of equation
255 (5) cannot be approximated as linear due to the high b_{vel} or ~~a transient~~an unsteady contribution caused the deviation.

In a recent work of the authors (Schulz et al., 2023), a small contribution of ~~transient~~transient unsteady aerodynamic phenomena to the torque and thrust response of the Vestas V80 rotor to surge motions was identified. While the unsteady airfoil correction of a BEMT method predicted a decrease of the load amplitudes due to the unsteady airfoil effect at high motion frequencies, panel method simulations showed a slight increase. This contradicting behaviour of the results of the methods was attributed
260 to unsteady, three-dimensional wake effects that cannot be covered by the BEMT.

When increasing the motion to inflow velocity ratio to extreme values, minimum and maximum power become more and more asymmetric to the mean value. Such behaviour is present in Tran et al. (2015) and Chen et al. (2021), where b_{vel} of 55 % or even higher have been investigated. This may be explained by the terms containing the third power of b_{vel} in the quasi-steady part of equation (A5) and does therefore not necessarily indicate ~~a transient~~an unsteady contribution.

265

In the above mentioned studies, the amplitude of the rotor thrust (and torque) response to a surge motion was mostly determined by a quasi-steady behaviour. However, some hints were found that the amplitudes may be deviated by ~~transient~~transient unsteady effects at high motion frequencies. Unfortunately, the influence of the potential ~~transient~~transient unsteady effects could not be investigated accurately in most cases, because the simulation cases did not allow for a clear distinction between these and
270 the quasi-steady effects.

3.2 Experimental investigations

A number of investigations considering FOWT rotors in motion have been conducted in the last decade. Most studies either address the influence of the motion on the wake development or the rotor loads. The most relevant studies that focus on the unsteady rotor loads are listed in table 2. As the model turbines are significantly downscaled, a scaling parameter for the
275 surge motion is mandatory. Many studies utilise the rotor reduced frequency for this purpose. However, it has to be noted that

Table 2. Experimental investigations on rotor loads of surging wind turbines.

Authors	Load measurements	Rotor diameter [m]	Wind speed [m/s]	Rotor reduced frequency* -	Motion to inflow velocity ratio* [%]	Norm. surge amplitude* [%]
Farrugia et al. (2014)	torque	0.46	8.0	0.02 - 0.05		
Sivalingam et al. (2018)	thrust, torque	1.00	0.8 - 1.2	0.18 - 0.89	3 - 53	2 - 12
Bayati et al. (2016)	thrust, torque	2.38	2.33 - 3.67	0.16 - 2.15	3 - 7	- 4
Bayati et al. (2018) and Mancini et al. (2020) and						
Fontanella et al. (2021)	thrust, torque	2.38	2.5 - 6.0	0.07 - 1.19	2 - 5	- 5
Meng et al. (2022)	thrust, power	0.18	4.9 - 7.1	- 0.01	- 4	10 - 20
Wei et al. (2022)	torque	1.17	8.0	0.36 - 0.83		
Fontanella et al. (2022), (2023)	thrust, torque	2.40	2.95 - 5.0	0.15 - 2.54	4 - 5	- 6
Schulz et al. (present)	torque	0.93	8.5	0.55 - 1.09	2 - 9	- 2

* at operation conditions near optimum TSR; measurement series 'RATED' for UNAFLOW campaign

from the three above mentioned ~~transient-unsteady~~ aerodynamic phenomena, only the dynamic inflow effect is covered by this choice.

Most studies utilise rotor diameters of 1 m and higher, because higher rotor diameters lead to higher rotor reduced frequencies at the same motion frequency. This is also necessary to maintain a high local Reynolds number at the blade, which is a prerequisite for reaching realistic power coefficients and good comparability between experiment and ~~full-scale~~ ~~full-scale~~ behaviour. As an exception, Farrugia et al. (2014) presented torque measurements of a combined wind tunnel and wave tank experiment of a model FOWT with a rotor diameter of 0.46 m. As the wind speed has been chosen to be comparatively high for wave tank experiments (8 m s^{-1}), a low maximum rotor reduced frequency of 0.047 resulted. Mean values and standard deviation of the measured torque were analysed for a large number of tip speed ratios (TSR) and different wave frequencies. Finally, no evidence for motion-induced torque fluctuations was found in the measurements, while FVW simulations clearly showed such fluctuations. Farrugia et al. noted that this mismatch is likely caused by the limited capabilities of the utilised torque meter.

One simple way to reach high wake reduced frequencies is to make use of an excessively low inflow wind speed. However, this usually leads to a significantly reduced flow quality and high uncertainties in the average wind speed as most wind tunnels are unable to reach and control a homogeneous flow at low wind speeds. In addition, the local Reynolds number at the blades becomes very small so that viscous contributions cause significant scale effects. Sivalingam et al. (2018) solved these issues by using water as flow medium, which increases the Reynolds number massively due to its low kinematic viscosity. The model rotor with a diameter of 1 m was mounted on a rigid carriage and towed through a towing tank at travel speeds around

1 ms⁻¹. An actuator mounted on the carriage realised the surge motion with different frequencies and amplitudes. In this way,
295 a maximum rotor reduced frequency of 0.89 could be achieved at a relatively low surge frequency of 0.89 Hz during normal
operation of the rotor at a TSR of 6. Torque and thrust have been measured directly at the shaft, but it was not mentioned
whether a correction of the inertial forces due to the surge movement was used. In addition to the experimental results, three
kinds of simulations utilising a RANS, a classical BEMT and a BEMT method with unsteady corrections are presented. While
the experiment at optimum TSR consistently shows a significantly higher thrust amplitude (between approx. 10 % and 25 %)
300 than the RANS and the classical BEMT simulations, the unsteady BEMT results do not follow a clear trend in comparison the
experiments. The measured mean thrust force scatters in a range of around 5 %, but no clear trend with the motion frequency or
motion to inflow velocity ratio could be identified. For torque oscillations at optimum TSR the simulation results are in better
agreement with each other, while the experiment again shows significantly higher amplitudes. It is interesting to note that
negative values for the measured rotor torque already occur at a motion to inflow velocity ratio of 13.5 %. RANS simulations
305 by Tran et al. (2015) and Lienard et al. (2020) show zero power output at motion to inflow velocity ratios above 70 % and 80 %
respectively. Unfortunately, a quantitative analysis of ~~transient~~unsteady contributions to torque and thrust amplitudes is not
given.

A series of experimental campaigns has been performed in the large wind tunnel of the Politecnico di Milano (PoliMi) using
a rotor with a diameter of 2.38 m. Maximum rotor reduced frequencies of up to 2.15 could be achieved for surge and pitch
310 motions in the first study (Bayati et al., 2016). Later, it was found that tower vibrations had a significant influence on the
measurements and a second campaign with a stiffer tower was performed within the UNAFLOW project (Fontanella et al.,
2021; Mancini et al., 2020), which focused on surge motions. The rotor thrust was measured by two triaxial force-moment
sensors at the tower top and tower base. At high motion frequencies, the measured thrust force was dominated by inertial
loads resulting from the tower top acceleration due to the surge motion. To remove the inertial loads from the thrust signal,
315 two compensation strategies were utilised: First, the inertial loads were determined in an experiment without wind and later
subtracted from the signal with wind (difference-based compensation). Second, the tower top acceleration was measured with
an accelerometer near the force-moment sensor and the inertial contribution was calculated from mass and actual acceleration
(acceleration-based compensation). However, in both cases the resulting thrust signal is extremely noisy due to tower vibrations
and other sources at higher surge frequencies (Mancini et al., 2020; Bayati et al., 2018), so that only amplitude and phase of
320 the first harmonic of the thrust signal were used as measurement result. Such data processing requires that the signal can be
considered as a mono-harmonic sine function in order to be accurate. Both compensations seem to be limited to a maximum
motion frequency as a result of the tower vibrations. While the thrust measurements were found to be reliable up to a reduced
frequency of approximately 0.9 for the difference-based compensation, a maximum reduced frequency of approximately 1.2
could be reached by the acceleration-based compensation (Mancini et al., 2020). In Fontanella et al. (2021), two measurement
325 series at rated turbine conditions (i.e. optimum TSR) are presented. The main difference between these series is the inflow
wind speed, which translates to a variation of the local Reynolds numbers at the blades. This difference seems to cause strong
deviations between the two series in the amplitude of the thrust force. The series with the higher wind speed is considered as
more reliable as unwanted viscous phenomena should have a reduced influence and a higher thrust force can be measured in this

case. An essentially linear relation between and the thrust amplitude ~~per-divided by the~~ motion amplitude and the rotor reduced
330 frequency was found up to a reduced frequency of around 0.6. For small motion amplitudes, this corresponds ~~the-to~~ a linear
relation between the thrust amplitude and the motion to inflow velocity ratio, which was also observed in some of the simulation
studies. For a higher reduced frequency, the scattering between the results for the different motion amplitudes is approximately
20 % of their mean value. As the results for the highest and the lowest motion amplitude are very similar while the two
intermediate motion amplitudes caused the highest and the lowest thrust amplitude, no physically meaningful interpretation of
335 the scattered results could be found. Therefore, these differences may be considered as measurement uncertainty. In Mancini
et al. (2020), where the acceleration-based compensation is applied, a very similar trend was observed. However, the scattering
seems to be slightly lower in this case. In both cases, no significant phase shift between the thrust force and the surge velocity
could be observed, while the interpretation of the phase angles was biased by a scattering of 5° to 10° . Mancini et al. noted
that the presented rotor torque measurements were strongly disturbed by a drive train resonance, which was at least present
340 for the two highest reduced frequencies. However, no clear, independent criterion was presented, which could identify the
border between the valid and the invalid measurement points. Therefore, also the results below a reduced frequency of 0.6
could be slightly affected by this distortion. An empirical model was tuned in order to compare the expected quasi-steady load
amplitudes against the measurements. The quasi-steady model tends to underpredict the measured load amplitudes in both
cases, however the scattering of the measurements at higher motion frequencies makes an evaluation difficult.

345 In the context of the COREWIND project, another model rotor was designed and subjected to surge motions in the wind
tunnel of PoliMi. The COREWIND rotor is very similar to the UNAFLOW rotor~~as the-~~ The same airfoil, nearly the same rotor
diameter and ~~a~~-similar operation parameters are utilised. Another test rig is used to impose the surge motion, which is also able
to perform 6-DOF motions in a limited frame. In Fontanella et al. (2022), motions in surge, sway, roll, pitch and yaw were
performed. For the surge motions, the difference-based inertia compensation is applied to the thrust measurements. Due to a
350 lower wind speed, a higher rotor reduced frequency compared to the UNAFLOW experiments could be reached in the tests. In
summary, three rotor reduced frequencies were tested: 0.14, 0.28 and 2.54. At the highest frequency, the measured thrust and
torque amplitudes were found to be around 30 % higher than the quasi-steady prediction of the empirical model. In case the
prediction is able to accurately represent the quasi-steady behaviour of the model rotor, this is a clear proof for a significant
contribution of ~~transient-unsteady~~ aerodynamic phenomena. Recently, another work of Fontanella et al. (2023) presents an
355 experimental investigation with a the same rotor containing a control system. Fontanella et al. mention a significant influence
of small rotor speed oscillations on the measured rotor torque amplitude. As a consequence of these oscillations, the torque
measurements are altered by inertial loads. The torque measurements are therefore corrected in a post processing step.

The investigations by Meng et al. (2022) and Wei et al. (2022) also include load measurements of a surging rotor. However,
these are not directly comparable to the present work, because of major differences in the measurement and/or data processing.

360 The above mentioned studies show that the measurement of rotor loads in surge motion is a challenging task. Vibrations lead
to a high random uncertainty or even biased measurement results at comparatively low rotor reduced frequencies. Nevertheless,
the linear trend of the rotor thrust amplitude with the motion to inflow velocity ratio could be proofed for low rotor reduced
frequencies in the PoliMi experiments. Latest results from the COREWIND project indicate that this is also the case for

moderate rotor reduced frequencies up to 1.7. A strong indication for transient effects could be found in another presentation
365 of the COREWIND campaign, but no confirmation by simulations or other sources is available so far.

4 Numerical methods and setups

The panel method *panMARE* and its ~~submodule~~ sub-module for lifting line calculations are utilised for the simulation of the three wind turbine rotors under consideration. In case of the IEA 15 MW rotor, additional BEMT simulations using OpenFAST are performed in order to evaluate the modelling of ~~transient~~ transient-unsteady phenomena in state-of-the-art BEMT methods during
370 a surge motion. For the sake of simplicity, the numerical methods are exclusively used to calculate aerodynamic loads, while inertia loads, rotor speed variations or controller actions are excluded from the ~~analysis~~ analysis. The utilised methods ~~and setups~~ are described briefly in the following sections. Details on the numerical setups for the individual rotors are given in appendix B.

4.1 *panMARE*: Panel method

375 The first-order panel method *panMARE* is an in-house development of the Hamburg University of Technology (TUHH) and has been utilised for floating structures and ship propellers (Bauer and Abdel-Maksoud, 2012) before it was extended to the simulation of FOWTs by Netzband et al. (2018). Validations were carried out with different wind turbine rotors and a verification with the results of the Offshore Code Comparison Continuation (OC4) campaign showed that combined aerodynamic, hydrodynamic and mooring loads as well as platform motions can be accurately captured (Netzband et al., 2018). *panMARE*
380 has also been utilised to develop and simulate the yaw mechanism of the passively yawing FOWT concept CRUSE Offshore SelfAligner (Netzband et al., 2020). A validation and verification with full-scale measurement data and simulations of the Floatgen prototype has been performed during the VAMOS project (Netzband et al., 2023).

In *panMARE*, the blade surface is discretised by panels. While source and doublet distributions are assigned to these panels, the three-dimensional wake is represented by doublet panels transported with the local wind speed (free wake). Panel methods
385 are based on the potential theory, which allows to describe the flow field as a boundary value problem. Therefore, viscous drag forces need to be considered by a viscous correction. In the present case, this correction is based on empirical airfoil drag coefficients of the blade sections. At every blade section, the inflow speed is calculated from the stagnation pressure. The effective angle of attack is then found by a comparison of the sectional lift force with the lift force of inviscid, two-dimensional simulations of the airfoil. Finally, the drag force of a section is calculated on the basis of local inflow velocity, effective angle of
390 attack and the empirical coefficients. A more detailed description of the panel method in conjunction with wind turbine rotors can be found in Netzband et al. (2018)

~~The TUHH model rotor is discretised by 2,940 blade surface panels and 9,600 wake panels, where the wake deformation is frozen after one rotor rotation. This represents a wake length of approximately 4 rotor diameters. The discretisation of the
395 wake is coarsened in 4 steps. Starting with a resolution of 1.26° azimuth angle per wake panel in tangential direction in the~~

direct vicinity of the trailing edge, which corresponds to a time step size of 0.0002 s. The tangential resolution of the near wake is approximately 10° per wake panel, while the discretisation of the far wake is 20° per wake panel in tangential direction. It has to be noted that the time step size is driven by the necessity to capture the surge motion in sufficient detail here. The cylindrical and transition blade sections near the root cannot be modelled in potential theory. Therefore, the blade starts at a relative radius of $r/R = 0.2$, where the blade is aerodynamically shaped. As the panel method is limited to inviscid flow, low Reynolds number regimes as seen in experiments often cause a slight overprediction of the lift force of the utilised airfoil. In case of the SD7062 airfoil, a simple lift correction could be applied in the panel method, which is described in appendix B1.

For the model of the IEA 15 MW rotor, 3,150 blade surface panels and 17,280 wake panels are used. A wake length of approximately 4 rotor diameters is covered by the wake panels. Three wake coarsening steps are applied so that a resolution of 3° per wake panel is reached near the blade. This corresponds to a time step size of 0.1 s. The resolution is 6° per wake panel in the near wake and 12° per panel in the far wake. The blade is modelled from a relative radius of $r/R = 0.18$.

4.2 *panMARE*: Lifting line method

A ~~submodule~~ sub-module for lifting line simulations was implemented in *panMARE* and used to efficiently generate initial wake geometries for propeller simulations in Wang and Abdel-Maksoud (2020). This ~~submodule~~ sub-module was slightly modified and adopted to wind turbines by the authors. In the ~~submodule~~ sub-module, the discretised blade surface is replaced by a simple lifting line at the 1/4 chord position and the wake is shed from the end of the chord line. In every time step, the local inflow velocity and angle of attack is determined from the flow field, which includes the influence of the wake and all inflow parameters. Then, the lift and drag forces are determined from empirical airfoil coefficients. Finally, the circulation of the lifting line is computed from the lift force. No unsteady corrections are used in the current version of the lifting line ~~submodule~~ sub-module. As described in section 2, these might be helpful for the incorporation of the non-circulatory unsteady airfoil effect as well as for the modelling of dynamic stall. However, both phenomena have minor influence in the considered cases.

The TUHH model rotor is discretised with the same resolution as in the panel method. Instead of the blade representation, a lifting line with 20 sections in spanwise direction is utilised. Lift and drag coefficients of the SD7062 were computed using Xfoil (Drela, 1989) for a local Reynolds number of 125 k. The two-dimensional simulations were validated against experimental data presented in Lyon et al. (1997) at slightly different Reynolds numbers and proofed excellent agreement. The UNAFLOW rotor is divided into 24 spanwise sections and a total number of 14,400 wake panels is utilised. This corresponds to a wake length of approximately 3 rotor diameters. A time step size of 0.002 s is applied, which corresponds to a angular resolution of 2.88° per time step. The wake resolution is approximately 6° in the near wake and 23° in the far wake. Lift and drag coefficients are chosen according to the description in Bergua et al. (2023).

4.3 OpenFAST

In BEMT methods, a momentum equilibrium on every annular ring of a wind turbine rotor is assumed. With this assumption, the rotor loads can be computed based on empirical lift and drag coefficients of the utilised airfoils. In contrast to FVW methods, the direct modelling of the flow field in the wake is not part of the method. The BEMT method AeroDyn v15, which is part of OpenFAST (v3.1.0), contains two unsteady corrections to correct for the unsteady airfoil and dynamic inflow effect. The unsteady airfoil correction is based on the Leishman-Beddoes model (Leishman and Beddoes, 1989) with slight modifications. The dynamic inflow correction based on Øye (see Snel et al. (1995)) prevents the axial induction from undergoing rapid changes. Further information on AeroDyn and its unsteady corrections is presented in Moriarty and Hansen (2005); Damiani and Hayman (2019) and Branlard et al. (2022).

~~In the model of the IEA 15 MW rotor, Prandtl tip and hub loss corrections as well as the unsteady airfoil and dynamic wake corrections are applied. The blade geometry and parameters for the unsteady airfoil correction published in the official github repository of the IEA 15 MW turbine⁵ were utilised in the simulations. It has to be noted that the coefficients A_1 , A_2 , b_1 and b_2 for the unsteady airfoil correction have originally been derived for a NACA0012 airfoil (Leishman and Beddoes, 1989). However, individualised coefficients for the various airfoil shapes at the blade sections have not been discovered in literature. For the dynamic inflow correction, the time constant τ_1 is chosen according to Øye (see e.g. Branlard et al. (2022)). The time step size is set to 0.1 s. A study on smaller time steps showed no noticeable influence of this particular choice on the results.~~

5 ~~Measurement campaign~~ Experimental and simulations corresponding numerical investigation of the TUHH rotor

5.1 Experimental setup

The experimental investigations were performed in the wind tunnel of the TUHH. Its test section is 2 m high, 3 m wide and 5 m long and the flow is characterised by a turbulence intensity below 0.5 %. A description of the wind tunnel environment and the TUHH model rotor can be found in a previous study of the yaw moment of the rotor (Schulz et al., 2022). Therefore, only a brief description on these topics is given in the following.

The two-bladed model wind turbine (see Figure 4) has a rotor diameter of 0.93 m. It is designed to be rigid so that no notable influence of blade bending and torsion on the load measurements is expected. The accuracy of the blade manufacturing was checked using a high-accuracy 3D surface scan. As scaled wind turbines generally suffer from a very low Reynolds number, the chord length is often significantly increased in comparison to the geometric scaling of ~~full-scale~~ full-scale turbines. This leads to a redesign of the complete blade geometry. Therefore, scale models can usually not be considered as certain turbine type anymore but serve as representatives for a typical modern wind turbine. In this case, a Reynolds number of approximately 125 k could be maintained over major parts of the blades due to the increased chord length and a comparatively high rotational speed of 1050 RPM during the measurements. In addition, the SD7062 airfoil was used for the whole blade, as laminar-turbulent

⁵<https://github.com/IEAWindTask37/IEA-15-240-RWT>, accessed at May 3rd, 2023




Figure 4. Photograph of the wind tunnel setup.




Figure 5. Sketch of the tower top of the test rig. The rotor nacelle assembly is mounted on a carriage, which can be moved in surge direction by the linear actuator.

transition occurs earlier compared to conventional wind turbine airfoils, which has a positive effect on aerodynamic properties at low Reynolds numbers.

460 Due to the specialised blade design, the occurrence of stall is not expected except very near to the root. All data to set up a numerical model of the rotor is given in Schulz et al. (2022).

— Sectional view of the nacelle. The load sensor (dark green) is integrated in the rotating shaft. The generator is illustrated in dark grey and the main bearings are coloured in blue. A slip ring is placed inside the shaft at its right end.

A novel test rig (see Figure 4) was developed in order to impose surge motions with high frequencies while minimising tower top vibrations. The key feature of the test rig is that the nacelle is mounted on a linear slide at the tower top (see Figure
 465




Figure 6. Power coefficient of the model rotor in dependence of the TSR. Lift and drag coefficients used in the simulations correspond to a Reynolds number of 125k.

5), which is connected to a magnetic linear motor. This allows to make use of a heavy and rigid tower design, while keeping the weight of the moving parts low. The steel tower with a height of 1 m consists of a base plate, a main column with a diameter of 0.1 m and a thickness of 6 mm and bracings that support the main column. The lowest eigenfrequency of the tower structure was found to be approximately 800 Hz in finite element simulations. ~~A sketch of the nacelle is given in Figure C1.~~ In order to reduce the inertia loads disturbing the thrust measurement, a 6-component force-moment sensor ~~(dark green in Figure C1)~~ was integrated into the rotating hub. Therefore, a wireless transmission of the measurement data was necessary. In addition, hall sensors, a surge position sensor and an accelerometer were placed in the nacelle. Details on the sensors and data acquisition [as well as a sketch of the nacelle](#) can be found in appendix C.

5.2 Steady operation conditions

475 In order to validate the capability of the simulation models to capture the quasi-steady behaviour of the model rotor, multiple test series with constant rotational speed and varying inflow wind velocity were performed and the experimental results were compared with those of the simulations. The three test series with rotational speeds of 600, 800 and 1050 RPM approximately correspond to local Reynolds numbers of 75 k, 100 k and 125 k at the blade sections. The measured values of the rotor torque were filtered for outliers, averaged over a period of 15 s and then utilised to compute the power coefficients, which are shown in Figure 6. For the highest Reynolds number, a maximum power coefficient of approximately 0.41 is reached, which confirms a comparatively low influence of undesirable viscous effects induced by the scaling. Therefore, a low sensitivity of local variations of the Reynolds number on the measured aerodynamic loads can be concluded. In addition, the smoothness of the curves gives a hint on a comparatively low repetition error, which was also observed in a previous investigation of this rotor (Schulz et al., 2022).

485 The lifting line simulations show a nearly exact agreement with the corresponding measurement series, while the panel method overpredicts the power coefficient slightly at low TSR. The operating point at which the surge tests were performed was selected to be at the highest rotational speed and a wind speed of 8.51 m s^{-1} . This corresponds to a TSR of 6 and optimal power generation.

5.3 Thrust measurements in surge motion

490 ~~Sinusoidal~~ Harmonic surge motions were applied to the model rotor at constant rotational speed and wind speed. An overview about the experimental load cases is given in table 3. The motion amplitudes and frequencies were chosen so that realistic motion to inflow velocity ratios for a FOWT in typical environmental conditions were covered. However, vibrations of the tower top limited the rotor reduced frequency to 1.09.

495 Although thrust measurements were recorded, a sufficiently low uncertainty could not be achieved. Accelerometer-based and difference-based inertia removal procedures were applied to separate the aerodynamic thrust force from the inertial forces of the rigid body. In the accelerometer based procedure, the nacelle acceleration was multiplied by the accelerated mass of the hub and subtracted from the axial rotor force. In the difference based procedure, the axial rotor force in surge motion was measured with and without wind. To gain the aerodynamic rotor thrust, the signal without wind was subtracted from the
500 signal with wind⁵. The inertia corrected thrust force signals were phase averaged over at least 10 periods and the thrust force amplitudes were extracted.

To check the integrity of the inertia force compensation procedures, a number of selected load cases were run multiple times without wind. Both procedures were applied to evaluate the measured values of test runs, which should result in a vanishing rotor thrust as no aerodynamic load was applied. In the covered motion range, the residual thrust amplitudes deviated up to
505 10 % of the nominal thrust from zero. Since the magnitude of the uncertainty is in the order of magnitude of the total thrust force amplitude at low b_{vel} , the determination of the ~~transient-unsteady~~ parts would be pursued as the identification of these parts of the load response require higher accuracy than in the measurements performed.

Forced tower top oscillations are considered as the main reason for the insufficient accuracy of the inertia removal procedures. These oscillations could not be filtered, because they occur exact at the same frequency as the inertia and aerodynamic
510 forces. Finally, it was found that the tower and support structure could not maintain a sufficiently low level of vibrations, although these were designed in a very rigid manner in comparison to other similar experimental set-ups. In contrast to this, torque measurements are less sensitive to tower top vibrations.

5.4 Torque measurements in surge motion

⁵In this procedure, aerodynamic loads on the rotor in the w/o wind cases are not considered. Due to the fact that the rotor is in standstill, these loads are assumed to be negligible.

Table 3. Surge motion load cases for the three different rotors. For the simulation studies, only minimum and maximum values for one series are given. Maximum values of periods and minimum values of amplitudes correspond to the same load cases and vice ~~versa~~versa.

	<i>absolute</i>				<i>dimensionless</i>		
	Wind speed	Rotational speed	Motion period	Motion amplitude	f_r	A/D	b_{vel}
TUHH rotor experiment	8.51 m s^{-1}	1050 RPM	0.2 s	5.10 mm	0.546	0.59 %	1.88 %
			0.2 s	10.1 mm	0.546	1.09 %	3.74 %
			0.2 s	15.1 mm	0.546	1.62 %	5.57 %
			0.125 s	5.30 mm	0.874	0.57 %	3.13 %
			0.125 s	10.5 mm	0.874	1.13 %	6.20 %
			0.125 s	15.7 mm	0.874	1.69 %	9.27 %
			0.1 s	5.50 mm	1.093	0.59 %	4.06 %
			0.1 s	10.9 mm	1.093	1.17 %	8.03 %
TUHH rotor extended	8.51 m s^{-1}	1050 RPM	0.0217 – 2.17 s	2.18 – 218 mm	5.04 - 0.0504	0.2344 - 23.44 %	7.42 %
			0.0217 – 2.17 s	3.26 – 326 mm	5.04 - 0.0504	0.3505 - 35.05 %	11.09 %
UNAFLOW rotor	4.19 m s^{-1}	240 RPM	0.0625 – 8.00 s	2.20 – 282 mm	9.09 - 0.071	0.0924 - 11.83 %	5.28 %
IEA 15 MW rotor	7 m s^{-1}	5 RPM	2.5 – 300 s	0.30 – 36.0 m	13.7 - 0.114	0.125 - 15.0 %	10.77 %

515 ~~Illustration of the data acquisition and inertia removal procedure for the torque measurements. Signal parts from load sensor measurements (top) and the rotational speed measurements (bottom) are added up in the last step.~~

Large effort was undertaken to keep an ideally constant rotor torque during the surge motion, however, a sinusoidal variation of the rotor speed in a range of 0.1 to 0.3 % of the nominal rotor speed could not be avoided. Due to the acceleration and deceleration of the rotor, the measured rotor torque contained a significant contribution of the corresponding rigid body inertia loads. In the present case, this contribution counteracted the aerodynamic rotor torque and therefore compensated the measured torque fluctuations to surprisingly small values. The same phenomenon was observed in the COREWIND experiments by Fontanella et al. (2023). As a consequence, an inertia compensation procedure needs to be applied to the torque measurements even for very small variations of the rotor torque. The aerodynamic rotor torque Q can be written as:

$$Q(t) = Q_{meas}(t) + J \frac{d\Omega}{dt}. \quad (12)$$

525 Where $Q_{meas}(t)$ is the measured torque and J describes the mass moment of inertia of the rotating part of hub and rotor behind the sensor. ~~As a prerequisite for the application of such compensations, the rotor speed oscillations need to be measured with high accuracy. The calculation procedure of the aerodynamic torque is illustrated in Figure C2. In the procedure, the rotational speed signal is phase averaged over at least 15 periods and than low pass filtered with an edge frequency of 2.5 times the motion frequency. Then, a central differencing scheme is applied to calculate the numerical derivative and the result is fed into equation~~

530 ~~The measured rotor torque is also phase averaged and filtered in~~ A number of post processing steps are required to reproduce
the actual aerodynamic torque from the ~~the same way. Finally, the aerodynamic rotor torque is calculated from equation load~~
and rotor speed measurements, which are described in appendix C2. The resulting rotor torque during one motion period is
shown in Figure 7 (blue line) for the cases listed in Table 3. It has to be noted that the aerodynamic torque signal follows a
mostly mono-harmonic trend, which is - in contrast to other experiments - not a result of a low pass filtering but the measured
535 characteristic of the signal. An estimation of the systematic uncertainty of this procedure is given in appendix D.

~~In Figure 7, the measured, phase averaged and filtered rotational speed variations as well as the compensated rotor torque are~~
~~shown for all load cases. Due to the low amplitude of the rotational speed oscillation, the signal is largely scattered. However,~~
~~the phase averaged results follow a sinusoidal trend in every case. Small disturbances of the gradient are disregarded using the~~
540 ~~low pass filtering. The aerodynamic torque signal follows a mostly mono-harmonic trend, which is not a result of the filtering~~
~~but the measured characteristic of the signal.~~

~~The extracted torque amplitudes~~ The torque amplitudes extracted from the time series signals are shown in Figure 8. The
amplitudes are normalised by the torque measured (or simulated) in steady conditions at the operation point. Only marginal
545 are considered. Every measurement was repeated at least twice⁶. The results for the same load case show very similar values,
which indicates a comparatively small repetition error. For selected load cases, also a third run was performed, which resulted
in similar values but are not shown here.

The same amplitudes are plotted over the corresponding motion to inflow velocity ratio b_{vel} and coloured by the rotor
reduced frequency in Figure 9. A linear ratio between the rotor torque amplitude and b_{vel} can be observed. This linear trend is
550 captured nearly exactly by both simulation methods. Interestingly, the variation of the rotor reduced frequency does not seem
to have any impact on this linear relation. Therefore, it can be clearly seen that b_{vel} determines the rotor torque amplitude,
when rotor speed and inflow speed are kept constant. This can be considered as proof that no transient-unsteady contributions
to the torque amplitude are present in these cases. It has to be noted that the absence of transient-unsteady behaviour can be
concluded from the independence of the linear trend from the motion frequency, however not necessarily from the presence of
555 a linear trend itself.

In Figure 10, the average rotor power derived from the rotor torque measurements normalised by the steady state power is
plotted over b_{vel} . The average power is computed by the product of the averaged rotor torque obtained by the load sensor and
the average rotational speed over approximately 15 motion cycles. A slight increase of the power can be observed with rising
 b_{vel} . In addition, comparatively strong scattering is visible, because the deviation from the steady state power is in a range
560 of only 1%. Again, no systematic influence of the motion frequency is detectable, which proves the absence of a-transient-an
unsteady influence on the average power. Both simulations agree closely with the measurements, which is not surprising as
it has been shown in Figure 6 that the quasi-steady power of the model rotor can be accurately captured by the simulations.
The deviations between measurements and simulations (also among each other) are within a maximum range of approximately

⁶Two cases are missing in the graph, because the rotational speed contained a significantly higher scattering in comparison to the other test runs.




Figure 7. Raw, phase averaged and filtered variation of the rotational speed measurements (left y-axis) and phase averaged, inertia-compensated rotor torque fluctuations (right y-axis).

0.4 %, which is considered as uncertainty.




Figure 8. Measured and simulated rotor torque amplitudes as response to 8 different surge motions. Values are normalised by the corresponding average rotor torque without motion. Two measurement runs under identical conditions are shown for most surge motions. A_D describes the motion amplitude normalised to the rotor diameter.




Figure 9. Measured and simulated rotor torque amplitudes as response to the surge motions plotted over the motion to inflow velocity ratio.

In summary, a precise agreement of measurements and the lifting line and panel method simulations in the steady and unsteady cases can be observed. No hint on transient-unsteady contributions to the rotor torque or any other transient-unsteady behaviour could be found in the experiments and simulations. Therefore, the rotor torque oscillations can be considered as quasi-steady and can be determined by b_{vel} exclusively in the applied range of motions and at constant rotor speed and wind inflow conditions. It has to be noted that only aerodynamic loads and no controller actions are considered here and in all following results.




Figure 10. Measured and simulated average power coefficient during the surge motions plotted over the motion to inflow velocity ratio.




Figure 11. Simulated rotor torque amplitudes of the model rotor as response to the extended surge motions plotted over the motion to inflow velocity ratio.

5.5 Simulation of extended motion parameters

6 Simulation study on the TUHH rotor beyond the experiment

The test rig was limited to moderate motion frequencies. In reality, significantly higher rotor reduced frequencies up to 8 or even higher may occur when considering 20 MW wind turbines moving with typical wave frequencies. Therefore, the surge motion frequency range was extended to investigate whether transient-unsteady aerodynamic effects may occur at very high motion frequencies. Figure 11 shows the normalised rotor torque amplitude over b_{vel} comparable to Figure 9, but with a higher range of the rotor reduced frequencies and b_{vel} .




Figure 12. Rotor torque amplitudes of the model rotor from simulations as response to the extended surge motions plotted over motion period and rotor reduced frequency. Torque amplitudes are normalised to the case with the highest motion period. The full-single (dark grey) and half-double (light grey) blade passing periods corresponding to f_{3P} and $1/2f_{3P}$ are indicated by vertical, dotted lines.

As in the previous case, a linear trend between the amplitude and the motion to inflow velocity ratio is present. The grey line
 580 representing a rotor reduced frequency of 0.5 is approximately equal to the previous experimental and numerical results and
 can therefore be considered as quasi-steady. The slope of the linear relation slightly rises for an increased reduced frequency
 of 1.9. Interestingly, a further increase to a reduced frequency of 3.8 yields a significant decrease of the slope. Finally, the
 results show a significant dependency of the rotor torque amplitude on the rotor reduced frequency at the same motion to
 inflow velocity ratio b_{vel} . This can be considered as proof of a-transient-an unsteady contribution to the load response of the
 585 simulations.

In order to characterise this transient investigate the underlying aerodynamic phenomenon causing this unsteady behaviour,
 a different kind of load case series is applied, which allows to investigate the influence of the motion frequency independent
 from b_{vel} . In these series, b_{vel} is kept constant, while the motion frequency varies (see Table 3). This results in a constant
 quasi-steady behaviour for every load case in the series while the influence of transient-unsteady phenomena may vary with the
 590 motion frequency. The load case with the lowest motion frequency is considered as an approximately quasi-steady case, because
 one surge motion period lasts as long as 35 rotor revolutions. The extremely low motion frequencies and their corresponding
 amplitudes therefore represent somewhat exaggerated cases, as such behaviour is not expected in reality.

The analysis in this section is based on the rotor torque for consistency with the experiments. As discussed in section 2.2,
the influence of the expected unsteady phenomena is very similar on torque and thrust in the case of surge motions. For
 595 completeness, the main results are also shown for the thrust force in appendix E. However, no principal difference between the
graphs for torque and thrust amplitudes can be found.

6.1 Analysis of the torque amplitudes

In Figure 12, the torque amplitude is displayed over the motion period and rotor reduced frequency. Two series with exemplary motion to inflow velocities were simulated with the panel method and the lifting line method. For visual purposes, the x-axis is chosen to be logarithmic. ~~AH~~In contrast to the preceding illustrations, all amplitudes are normalised to the quasi-steady case, which corresponds to the amplitude at a rotor reduced frequency of 0.02 (or a period of 2 s). This also applies to all following sections. The normalised rotor torque Q_{amp}^* therefore describes the ratio between the actual torque amplitude Q_{amp} and the torque amplitude of the simulation case with the longest motion period $Q_{amp,qs}$:

$$Q_{amp}^* = \frac{Q_{amp}}{Q_{amp,qs}}. \quad (13)$$

This results in the fact that all curves reach 1 at this period.

Starting on the right at the lowest reduced frequency, both methods show a slowly increasing torque amplitude up to a reduced frequency of 2. A rapid drop of approximately 30 % occurs towards a reduced frequency of 4, which is followed by another increase. This behaviour clearly indicates the presence of ~~transient-unsteady~~ aerodynamic phenomena. Otherwise, all curves would follow a constant trend over the rotor reduced frequency. From the displayed results it is difficult to conclude, which of the ~~above-described transient aerodynamic phenomena~~ unsteady aerodynamic phenomena described in section 2.2 may cause such behaviour. However, the minimum amplitude is reached at the surge motion frequency that corresponds to the blade passing frequency (35 Hz i.e. a period of 0.0286 s). This provides a strong indication that the returning wake effect is present.

6.2 Identification of the returning wake unsteady airfoil effect in 2D

The returning wake effect can be modelled in a two-dimensional manner using the cascade approach, which was demonstrated for wind turbines by Eliassen (2015). Therefore, an equivalent two-dimensional setup approximately corresponding to the flow situation on a cylindrical surface with a relative radius of 62 % was created in *panMARE* (see Figure 13). For the sake of simplicity, only two airfoils representing the two blade sections were considered here. However, for a complete representation of the returning wake effect in such setup, multiple airfoils and their wakes would be necessary. The two airfoils in Figure 13 represent cuts through the two blades at a constant radius as indicated by the black contours in Figure 2⁷. Their distance in lateral direction to each other equals the arc length from one blade to the other in the three-dimensional case. In consequence, the interaction of the shed vortices from the first blade with the lift force of the second blade at a given blade section can be represented in this way. However, due to the limitation to two airfoils, only the vortices shed during one rotor rotation are

⁷The present analysis is limited to the influence of the shed wake of the first blade to the second blade during the first rotor rotation. However, due to the modelling constraints of the cascade approach, a third airfoil has to be placed in the row in order to evaluate the lift force of the second airfoil in a physically correct way (see Eliassen (2015) for details). This third airfoil is present in the simulations but not shown in the figure for the sake of simplicity.




Figure 13. Schematic setup of the two-dimensional simulations of a blade section. The setup can be considered as unrolled version of the sectional view illustrated in black in Figure 2. l and β describe the distance between the two airfoils and the local twist angle at the corresponding rotor radius.




Figure 14. Lift amplitudes of an airfoil undergoing a plunging motion. Amplitude and frequency of the motions are chosen corresponding to the flow situation at a rotor radius of 62 % of the model rotor undergoing the surge motions presented in Table 3. Results are shown for the a setup with one and two airfoils. In case of two airfoils, the lift amplitude of the second airfoil is plotted. Lift amplitudes are normalised to the case with the highest motion period.

625 considered in the two-dimensional simulations. The inflow speed and angle of attack of the airfoils approximately correspond to those in the three-dimensional simulations. The surge motion is represented as a harmonic vertical motion of the airfoil pair.

The lift force amplitude of the second airfoil for different motion frequencies is shown Figure 14. In addition to that, the results for the same setup with only one airfoil, where no returning wake effect is present, can be seen in the graph. Again, the amplitudes are normalised to the largest motion period (corresponding to the lowest rotor reduced frequency), which can
 630 be considered as a quasi-steady case. This assumption can be confirmed by the nearly horizontal slope of the amplitudes at

the highest motion period. On the top border of the graph, a second scale indicating the airfoil reduced frequency is inserted. The lift amplitude of the single airfoil follows a decreasing trend from an airfoil reduced frequency of 0.02. This decrease is in accordance with simulations presented by Leishman (2000) and can be explained by the circulatory unsteady airfoil effect. The slight differences between the panel method and the lifting line simulations may be caused by the insufficient representation
635 of the blade utilising a point vortex in the lifting line method. When two airfoils are considered, the characteristic of the lift amplitude is similar to the torque amplitude of the rotor. The maximum is reached when the motion frequency equals half the blade frequency and a drop of around 30 % is present when the motion frequency equals the blade frequency. As the setup shown in Figure 14 corresponds to the schematic illustration in Figure 1, the occurrence of the maximum and minimum can be explained in the same way as done in section 2.

640 Finally, the characteristic of the rotor torque amplitude can be approximately reconstructed at a representative two-dimensional blade section. The occurrence of the minimum at the blade frequency can be clearly attributed to the returning wake effect. This observation provides a strong indication that the driving aerodynamic phenomena are the unsteady airfoil and the returning wake effect. The less pronounced maximum may be explained by fact the torque is a the summation of the sectional load responses, which may not have the exact same characteristic at different blade spans. Another reason might be the limitation
645 of the two-dimensional simulations to two airfoils.

It is unclear at this point whether or in which frequency range the dynamic wake effect comes into play. Regarding the two different motion to inflow velocity ratios tested, it seems that the chosen b_{vel} has negligible influence on the ~~occurrence of the transient aerodynamic behaviour~~ unsteady aerodynamic behaviour of the rotor torque, because nearly no difference between the corresponding curves is present. This is in line with the conclusions drawn from similar simulations of the FLOATGEN
650 wind turbine using a panel method and a BEMT method (Schulz et al., 2023).

6.3 Phase shift of the rotor torque

In Figure 15, the phase shift between the torque oscillation and the surge position is shown. In case of the rotor torque, an initial phase shift of 90° is present at the lowest rotor reduced frequency, which means that the torque oscillation is in phase with
655 the motion velocity. The phase shift stays constant up to a rotor reduced frequency of 1 and then increases until a maximum is reached slightly below 4. With further rising reduced frequency, the phase shift drops approximately 20° . Lifting line and panel method simulations agree well up to a reduced frequency of 3. At higher reduced frequencies, a difference of around 10° evolves. The characteristic behaviour is in line with the phase shift of the lift force in the two-dimensional case (see Figure 16), when the second airfoil is considered. Therefore, the characteristic of the phase can also be attributed to a superposition
660 of the unsteady airfoil and the returning wake effect. Interestingly, the difference between the lifting line and the panel method simulations is also present in the simulations, where only one airfoil is considered. In this case, the unsteady airfoil effect determines the ~~transient unsteady~~ behaviour. The difference at higher airfoil reduced frequencies can most likely be attributed to the non-circulatory unsteady airfoil effect, which cannot be modelled by the lifting line method.




Figure 15. Phase shift between rotor torque and surge position ~~correspiong~~ corresponding to amplitudes of the model rotor shown in Figure 11.




Figure 16. Phase shift between lift and surge position ~~correspiong~~ corresponding to amplitudes of two-dimensional simulations shown in Figure 14.

665 ~~When considering the thrust force oscillation caused by the imposed surge motion, a nearly identical behaviour can be observed in the graphs in appendix E. This is straight forward, because both, torque and thrust, are driven by the lift force fluctuations.~~

7 Simulation ~~studies~~ study on the UNAFLOW ~~and the IEA 15 MW rotors~~ rotor

~~In order to investigate whether the occurrence of the returning wake effect is caused by the individual characteristic of the TUHH model rotor or generally needs to be taken into account, the behaviour of two other exemplary rotors is analysed.~~

670




Figure 17. Rotor thrust amplitudes of the UNAFLOW rotor from simulations as response to surge motions plotted over motion period and rotor reduced frequency. Thrust amplitudes are normalised to the case with the highest motion period.

7.1 UNAFLOW rotor

The *panMARE* lifting line model, which was set up in the OC6 project, is utilised to run a load case set with extended motion frequency range in comparison to previous studies. As ~~most previous investigations on wind turbine rotors in surge motion focus on the thrust force, the same is done in the following investigation. However~~ the similarity between results of the lifting line and the panel method has already been shown for the TUHH rotor, the existing model was used only. In order to allow for a more direct comparison with other studies, the following analysis is based on the thrust force. As discussed above, the behaviour of ~~the torque amplitudes was found to be very similar and is shown~~ torque and thrust amplitudes is very similar. The results for torque can be found in appendix F.

In Figure 17, the normalised thrust amplitude of the UNAFLOW rotor as a response to a series of surge motions with a constant motion to inflow ratio and varying rotor reduced frequency is shown. The motion to inflow velocity was chosen to be $b_{vel} = 5.28\%$, which corresponds to a load case from the measurement campaign. The load cases are listed in Table 3. As in the previous figures, the amplitudes are normalised to the case with the lowest rotor reduced frequency i.e. highest motion period. It is shown, that the amplitude stays approximately constant in the range of low rotor reduced frequencies. From a rotor reduced frequency of 0.5, the curve rises again slightly and reaches a flat maximum at half the blade passing frequency followed by a rapid decrease with a minimum at the blade passing frequency. Apart from the slight decrease at low motion frequencies, a very similar behaviour as seen for the TUHH rotor can be identified. The same is true in case of the phase shift of the thrust oscillation shown in Figure 18. However, the maximum phase shift is about 10° higher in comparison to the TUHH rotor. As the lifting line method showed an overprediction of the maximum phase angle in case of the TUHH rotor, it is likely that the same is true for the UNAFLOW rotor. Due to the characteristic behaviour of the thrust amplitude, it can be concluded that the returning wake effect also has a significant influence on the UNAFLOW rotor in surge motion.




Figure 18. Phase shift between rotor thrust and surge position ~~correspieng~~corresponding to amplitudes of the UN-AFLOW rotor shown in Figure 17.

A hint on such behaviour can also be found in Ribeiro et al. (2023). Panel method simulations showed a lower-than-expected thrust amplitude at a rotor reduced frequency slightly below 5. This is in line with the decrease of the amplitude in the range of the rotor reduced frequencies between 3 to 7 shown in the present simulations. Ribeiro et al. assumed that this drop is caused by a varying phase shift of the lift force variation over the blade span (see section 3). However, from the two-dimensional
 695 investigations shown in the previous section and the characteristic occurrence of minimum and maximum it seems more likely that the returning wake effect induces this behaviour.

In the measurements performed during the UNAFLOW project, no such behaviour of the thrust amplitude was observed. This is in line with the present simulation results as the measurements in Mancini et al. (2020) were limited to reduced a maximum reduced frequency of 1.19. In this region, only limited influence of ~~transient~~transient-unsteady effects can be seen in Figure
 700 17. Also other previous simulation studies including OC 6 Phase III (Bergua et al., 2023) were limited to a similar motion frequency range, so that - apart from a slight phase shift - no ~~transient~~transient-unsteady behaviour could be noticed.

In contrast to this, unexpected thrust and torque amplitudes were observed during the COREWIND measurement campaign (Fontanella et al., 2022). At a rotor reduced frequency of approximately 2.5, these were approximately 30 % higher than expected from a quasi-steady model. As the rotor, operational conditions, wind speed and load case set are quite similar to
 705 the UNAFLOW campaign, it can be assumed that at least a similar characteristic behaviour of both rotors should be present. However, the present simulations seem to contradict the measurements. The reason for this is not quite clear and further simulations on this specific rotor as well as continued experimental efforts may shed light on this interesting observation.

7.1 IEA-15 MW

8 Simulation study on the IEA 15 MW turbine




Figure 19. Calculated rotor thrust amplitudes of the IEA 15 MW as a response to surge motions plotted over motion period and rotor reduced frequency. Thrust amplitudes are normalised to the scenario with the highest motion period in case of the panel method and to the quasi-steady simulation in case of the BEMT.




Figure 20. Lift amplitudes of an airfoil undergoing a plunging motion. Amplitude and frequency of the motions are chosen corresponding to the flow situation at a rotor radius of 64 % of the IEA 15 MW rotor undergoing the surge motions presented in table 3. Results are shown for the a setup with one and two airfoils. In case of two airfoils, the lift amplitude of the second airfoil is plotted. Lift amplitudes are normalised to the case with the highest motion period.

710 ~~The IEA 15 MW wind turbine is investigated as it is a representative for modern, large size wind turbines.~~ A set of load cases with a constant motion to inflow velocity ratio and varying surge motion frequency is applied to the [IEA 15 MW](#) rotor (see Table 3). The thrust force amplitudes calculated by the panel method and the BEMT method over a wide range of motion periods are shown in Figure 19. The characteristic change of the thrust force amplitude is similar to those of the model rotors. However, no distinct maximum can be identified at the surge motion frequency, which equals half the blade passing frequency.

715 In order to investigate this difference, two-dimensional flow simulations around the blade sections of the IEA 15 MW rotor
at an exemplary relative radius of 0.64 were performed. The setup was chosen in the same way as in section 6. In Figure 20,
the lift amplitude of the second airfoil as a response to the surge motion is shown. A characteristic similar to the one in the
previous two-dimensional simulations can be identified. However, the minimum and maximum are less pronounced in this
case. Similarly, the decrease of the lift amplitude in the case of a single airfoil is less strong. This can be explained by the
720 lower range of the airfoil reduced frequency (see upper x-axis) in comparison to Figure 14. For example, at the blade passing
frequency, the airfoil reduced frequency is 0.07 for the IEA 15 MW airfoil while it is 0.2 for the TUHH rotor airfoil⁸. The
unsteady airfoil effect is therefore much stronger in case of the TUHH rotor at the same ratio of motion and blade passing
frequency. As the returning wake effect is driven by the same vortices shed from the trailing edge of the upward blade, it is
straight forward that it is also less pronounced in this case. The influence of the returning wake effect may be considered as a
725 perturbation of the unsteady airfoil effect on the lift amplitude of an oscillating airfoil.

It has to be noted that the two-dimensional simulations only represent the flow at one specific rotor radius. Therefore,
the lower height of the maximum peak in these simulations may be understood as a hint that the returning wake effect is
less pronounced in case of the IEA 15 MW rotor, which most likely leads to the absence of a maximum in the rotor thrust
amplitude. In addition, the two-dimensional simulations indicate that unsteady airfoil and returning wake effect already act on
730 the sectional blade loads between 10 s and 20 s although the trend of the rotor thrust amplitude is nearly constant in this region.
Therefore, a simulation method that only covers the unsteady airfoil effect, might predict erroneous amplitudes in this region.

The results of the BEMT simulations are illustrated by three different lines in Figure 19. A normalisation of the thrust force
amplitudes to the quasi-steady results is applied. The BEMT without unsteady corrections (BEMT qs) shows a constant trend,
which due to its quasi-steady nature. With the application of the dynamic inflow correction (BEMT dyn. inflow), the normalised
735 amplitude shows a continuously decreasing trend with decreasing motion period. This decrease changes to a constant trend for
motion periods lower than 20 s. The unsteady airfoil correction causes an additional decrease of the thrust amplitude at motion
periods below 15 s. While the effect of the unsteady airfoil correction is similar to the trend of the single airfoil in Figure 20,
the returning wake effect is naturally not captured by the unsteady corrections. Furthermore, it is remarkable that the dynamic
inflow correction causes such strong decrease of the thrust amplitude, because this is not in line with the panel method. In
740 addition, the panel method seems to converge against a quasi-steady value for periods above 200 s, while the dynamic inflow
correction in the BEMT simulations still contributes to the amplitude at a period of 300 s. As the panel method inherently
captures the dynamic inflow effect, it is likely that the dynamic inflow correction of the BEMT method may not be suitable in
this case. The unsteady airfoil correction of the BEMT method seems to capture the general trend of the phase shift well, while
the returning wake effect is naturally not captured.

745 In Figures 21 and 22, the phase shift of the rotor thrust oscillation and the lift force in 2D in comparison to the surge position
are shown. Again, a similar characteristic can be identified.

⁸Note that the airfoil reduced frequency is dependent on the chord length and consequently on the rotor radius. Therefore, this comparison is only valid
because both simulations represent the situation at approximately the same relative radius.




Figure 21. Phase shift between rotor thrust and surge position ~~correspieng~~ corresponding to amplitudes of the IEA 15 MW rotor shown in Figure 19.




Figure 22. Phase shift between lift and surge position ~~correspieng~~ corresponding to amplitudes of two-dimensional simulations shown in Figure 20.

9 Characterisation and occurrence of ~~transient~~ transient-unsteady aerodynamic phenomena

9.1 Characterisation

The unsteady airfoil effect and the returning wake effect could be identified as major drivers for ~~transient~~ transient-unsteady contributions to the load response of surging wind turbine rotors. In particular, the circulatory part of the unsteady airfoil effect was dominant over the non-circulatory part. A significant contribution of the dynamic inflow effect could not be found in the free vortex wake simulations. However, no special investigations aiming at this were performed in this study.

The occurrence and strength of these transient-unsteady aerodynamic phenomena can be estimated by the dimensionless numbers described in section 2. In case of the airfoil reduced frequency, it is difficult to find a representative value for the rotor as it varies over the blade span due to its dependency on the chord length. Transient-Unsteady contributions to the load response were identified at an airfoil reduced frequency of 0.02 and higher in the investigated cases two-dimensional simulation cases for the TUHH and the IEA 15 MW rotors. This differs slightly from the limiting value (0.05) given by Leishman (2000). The strength of the returning wake effect is strongly influenced by the airfoil reduced frequency and the ratio of surge motion frequency and blade passing frequency. In case the airfoil reduced frequency is sufficiently high, the returning wake effect comes into play when the motion frequency rises above half the blade passing frequency or even at slightly lower values. However, it seems that in practisepractice, an airfoil reduced frequency of above 0.02 is a prerequisite for the occurrence of the returning wake effect. The strength of the returning wake effect is also affected by the distance between the blade sections and the wake sheet from the upward airfoil i.e. from the pitch of the helical wake.

Finally, an experimental wind turbine rotor would need to maintain similarity with all three dimensionless numbers from described in section 2 in order to model the occurrence of these transient-unsteady aerodynamic phenomena comparable to a full-scale full-scale turbine. The consideration of the rotor reduced frequency only is therefore not sufficient. This can be easily recognised by comparing the load response amplitudes of the three rotors (Figures 12, 17 and 19). The minima in these cases clearly not occur at the same rotor reduced frequencies.

9.2 Occurrence in full scale

In practisepractice, the investigated pure surge motion is superposed with a rotor speed oscillation in below rated conditions. The rotor speed oscillation has shown to trigger a strong dynamic inflow effect even at low motion frequencies in a previous work (Schulz et al., 2023). However, the observed phenomena will most likely also occur, when a concurrent rotor speed variation is present. The returning wake effect may occur at large turbines in low wind speed conditions, where half the blade passing frequency may be in a range of the wave spectrum. As seen in the case of the IEA 15 MW at 7 m.s^{-1} wind speed, the returning wake effect impacts the sectional lift force at a motion period of 10 s. This is within the range of typical wave periods (approximately 5 - 20 s). However, a prediction of the quantitative impact of the returning wake effect from the dimensionless numbers is challenging and therefore exemplary FVW simulations at low wind speeds might give a more reliable insight.

10 Summary and conclusions

An experimental and numerical investigation on the occurrence of transient-unsteady aerodynamic phenomena caused by a surge motion of a wind turbine rotor is presented. The investigation is limited to aerodynamic loads and basic surge motion scenarios scenarios excluding rotor speed variations or controller actions. To impose a surge motion to the two-bladed TUHH model rotor, a novel test rig was designed. The surge motion is applied to the nacelle only, which allows for a very rigid tower design. In addition, the load sensor was placed in the shaft of the rotor to reduce undesirable inertia forces in the measurement signal. The results of FVW lifting line and panel method simulations utilising the software *panMARE* were compared against

785 those of the measurements. In a second step, the simulations were extended to a frequency range exceeding the capabilities of
the test rig and certain load cases were investigated to distinguish between the quasi-steady and the ~~transient-unsteady~~ part of
the load response to a surge motion. In order to proof the generality of the findings, the load case set was additionally applied to
the UNAFLOW and the IEA 15 MW rotors. Additional BEMT simulations of the IEA 15 MW rotor with and without unsteady
corrections were conducted. Finally, a characterisation of the observed ~~transient-unsteady~~ aerodynamic phenomena is given
790 and the applicability of three dimensionless numbers to identify their occurrence is discussed.

The most relevant findings from the numerical and experimental investigations can be summarised as follows:

- Despite the comparatively rigid tower design and two different approaches to remove inertial loads from the axial force
measurements, a sufficient accuracy of the compensated rotor thrust force could not be achieved ~~due to~~. This was most
likely caused by forced vibrations of the tower top.
- 795 – Slight oscillations of the rotor speed were found to have major influence on the measured rotor torque. Therefore, an
inertia removal procedure was developed and applied. The compensated measurements proofed to have a low repetition
error and very good agreement with the FVW simulations. This is the case for steady and unsteady scenarios.
- The measured torque oscillation amplitudes during surge motions were found to be determined by the motion to in-
flow velocity ratio b_{vel} and can therefore be considered as quasi-steady in the motion frequency range covered by the
800 experiments (f_r between 0.55 and 1.09, b_{vel} up to 9%).
- The extension of the motion frequency range in the FVW simulations up to a reduced frequency of 5 revealed a significant
influence of the returning wake effect on both amplitude and phase of the torque and thrust force. Therefore, ~~transient~~
unsteady aerodynamic phenomena are clearly present in the simulations.
- The occurrence of the returning wake effect could also be proofed in case of the UNAFLOW and the IEA 15 MW
805 rotor. In case of the IEA 15 MW, ~~transient-unsteady~~ contributions to the torque and thrust response were found within
the frequency range of common seaways at reduced frequencies between 3 to 7. The returning wake effect had a
clear influence on the airfoil loads at motion frequencies in the range of half the blade passing frequency and higher. A
prerequisite for its occurrence seemed to be an airfoil reduced frequency ~~of more than~~ above 0.02.
- The ~~transient-unsteady~~ aerodynamic behaviour was determined by the circulatory unsteady airfoil effect and the returning
810 wake effect in the investigated cases. A contribution of the dynamic inflow effect was not investigated in detail. Therefore,
a proper scaling of these effects would need to maintain similarity between the corresponding dimensionless numbers
described in section 2. Utilising the rotor reduced frequency only for this purpose was found to be not sufficient.
- BEMT simulations with and without common unsteady corrections were naturally unable to capture the returning wake
effect. Instead, an impact of the dynamic inflow effect was present at comparatively low motion frequencies i.e. rotor
815 reduced frequencies. This is not in line with the FVW simulations and may indicate a limited suitability of the dynamic
inflow correction in the investigated cases.

It has to be noted that the above mentioned findings regarding the transient-unsteady aerodynamic phenomena are based on two FVW methods that utilise the same software routines in major parts. In addition, attached flow conditions were assumed in all cases. In case of the IEA 15 MW rotor, this might have deviated the results slightly. Therefore, all findings need to be evaluated
 820 using other FVW methods, higher fidelity simulations and experiments. Special attention should be paid to a comparison of high fidelity simulations and/or experiments with the COREWIND measurements, where a contradicting trend in comparison to the present simulations was found.

In practisepractice, the returning wake effect is most likely present in case of large rotors and low inflow wind speeds. Most state-of-the-art BEMT methods are not capable of modelling the returning wake effect. Therefore, FVW simulations are
 825 strongly recommended to check whether its influence is significant and the application of such methods is valid in these cases.

Appendix A: Derivation of equation (4)

In section 2, the amplitude of the rotor power oscillation caused by a harmonic surge motion at constant wind speed and constant rotational speed is stated (see equation (4)). As a basis, the well-known empirical formulation for the steady power of a wind turbine is adopted to a sinusoidal variation of the inflow speed in equation (2), where potential transient-unsteady
 830 effects are summarised in the extra term $P_{\underline{trans}}(t)P_{\underline{unsteady}}(t)$. When introducing the dimensionless number b_{vel} , equation (2) can be rewritten as:

$$P(t) = \frac{\rho A v_0}{2} \frac{\rho A v_0^3}{2} C_p(\lambda(t)) (1 + b_{vel} \sin(2\pi ft))^3 + P_{\underline{transunsteady}}(t). \quad (A1)$$

Furthermore, the quasi-steady amplitude of the rotor power can be computed by the difference of the minimum and the maximum power during a surge motion cycle, which occur at minimum and maximum motion velocity.

$$835 \quad P_{amp} = \underbrace{\frac{\rho A v_0^3}{2} \frac{1}{2} C_{p,v_{max}} (1 + b_{vel})^3 - C_{p,v_{min}} (1 - b_{vel})^3}_{\text{quasi-steady}} + \underline{transient} \underbrace{\Delta P_{\underline{unsteady}}}_{\underline{unsteady}}. \quad (A2)$$

As the steady power coefficient is determined by the actual inflow velocity and the rotational speed, its values at the highest and lowest motion velocities can be determined simply.

$$C_{p,v_{max}} = C_p(v_0(1 + b_{vel}), \Omega) = C_p(\lambda_{min}) \quad (A3)$$

$$840 \quad C_{p,v_{min}} = C_p(v_0(1 - b_{vel}), \Omega) = C_p(\lambda_{max}) \quad (A4)$$

λ_{min} and λ_{max} correspond to the minimum and maximum λ TSR that is reached during a surge motion cycle. When finally introducing equations (A3) and (A4) into (A2), equation (4) results.

For small b_{vel} , C_p may be assumed to be constant. In this case, equation (4) can be simplified to:

$$P_{amp} = \frac{\rho A v_0^3}{2} \frac{1}{2} C_p(\lambda) (3b_{vel} + b_{vel}^3) + \Delta P_{\text{transunsteady}} \quad (\text{A5})$$

845 As the third power of b_{vel} may be disregarded in this case, a linear trend of the power amplitude with b_{vel} results in the quasi-steady case. Due to the constant rotor speed, the torque amplitude is linearly dependent on the power amplitude. Analogously, the thrust amplitude can be expressed as:

$$T_{amp} = \frac{\rho A v_0^2}{2} \frac{1}{2} C_t(\lambda) (2b_{vel} + b_{vel}^2) + \Delta T_{\text{transunsteady}} \quad (\text{A6})$$

However, the limitations of these simplifications need to be evaluated in the considered application case.

850 **Appendix B: Lift correction in panMARE Details on numerical methods and models**

B1 Lift correction in panMARE

Panel methods often suffer from an overprediction of the lift force, when airfoils at low Reynolds numbers are considered. In case of the SD7062 airfoil used for the TUHH model rotor at a Reynolds number of 125 k, this overprediction can be approximated as a constant offset up to an angle of attack of 5° (see Figure B1). The angles of attack along the blade span
855 during the surge motion tests range from approximately 1° to 4.5° at 90 % of the blade. In this region, an offset of the angle of attack of about 0.8° is sufficient to correct the overprediction of the lift coefficient (see 'panMARE panel, corrected' in Figure B1), which is applied in the presented simulations of the TUHH model rotor.

B2 Numerical setups in panMARE (panel method)

The TUHH model rotor is discretised by 2,940 blade surface panels and 9,600 wake panels and the wake deformation is
860 'frozen' after one rotor rotation. This represents a wake length of approximately 4 rotor diameters. The discretisation of the wake is coarsened in 4 steps. Starting with a resolution of 1.26° azimuth angle per wake panel in tangential direction in the direct vicinity of the trailing edge, which corresponds to a time step size of 0.0002 s. The tangential resolution of the near wake is approximately 10° per wake panel, while the discretisation of the far wake is 20° per wake panel in tangential direction. It has to be noted that the time step size is driven by the necessity to capture the surge motion in sufficient detail here. The
865 cylindrical and transition blade sections near the root cannot be modelled in potential theory. Therefore, the blade starts at a relative radius of $r/R = 0.2$, where the blade is aerodynamically shaped. As the panel method is limited to inviscid flow, low Reynolds number regimes as seen in experiments often cause a slight overprediction of the lift force of the utilised airfoil. In case of the SD7062 airfoil, a simple lift correction could be applied in the panel method, which is described in appendix B1.
For the model of the IEA 15 MW rotor, 3,150 blade surface panels and 17,280 wake panels are used. A wake length of
870 approximately 4 rotor diameters is covered by the wake panels. Three wake coarsening steps are applied so that a resolution of 3° per wake panel is reached near the blade. This corresponds to a time step size of 0.1 s. The resolution is 6° per wake panel in the near wake and 12° per panel in the far wake. The blade is modelled from a relative radius of $r/R = 0.18$.




Figure B1. Lift coefficient of the SD7062 airfoil computed with Xfoil and *panMARE* in comparison with the applied correction. Dotted red lines indicate the range of realistic angles of attack of the TUHH model rotor in the present operating conditions.

B3 Numerical setups in *panMARE* (lifting-line method)

875 The TUHH model rotor is discretised with the same resolution as in the panel method. Instead of the blade representation, a lifting line with 20 sections in spanwise direction is utilised. Lift and drag coefficients of the SD7062 were computed using Xfoil (Drela, 1989) for a local Reynolds number of 125 k. The two-dimensional simulations were validated against experimental data presented in Lyon et al. (1997) at slightly different Reynolds numbers and proofed excellent agreement. The UNAFLOW rotor is divided into 24 spanwise sections and a total number of 14,400 wake panels is utilised. This corresponds to a wake length of approximately 3 rotor diameters. A time step size of 0.002 s is applied, which corresponds to
 880 a angular resolution of 2.88° per time step. The wake resolution is approximately 6° in the near wake and 23° in the far wake. Lift and drag coefficients are chosen according to the description in Bergua et al. (2023).

B4 Numerical setups OpenFAST

885 In the model of the IEA 15 MW rotor, Prandtl tip and hub loss corrections as well as the unsteady unsteady airfoil and dynamic wake corrections are applied. The blade geometry and parameters for the unsteady airfoil correction published in the official github repository of the IEA 15 MW turbine⁹ were utilised in the simulations. It has to be noted that the coefficients A_1 , A_2 , b_1 and b_2 for the unsteady airfoil correction have originally been derived for a NACA0012 airfoil (Leishman and Beddoes, 1989). However, individualised coefficients for the various airfoil shapes at the blade sections have not been discovered in literature.

⁹<https://github.com/IEAWindTask37/IEA-15-240-RWT>, accessed at May 3rd, 2023




Figure C1. Sectional view of the nacelle. The load sensor (dark grey) is illustrated in dark grey and the main bearings are coloured green.

For the dynamic inflow correction, the time constant τ_1 is chosen according to Øye (see e.g. Branlard et al. (2022)). The time step size is set to 0.1 s. A study on smaller time steps showed no notable influence of this particular choice on the results.

890 Appendix C: Data acquisition

C1 Actuation and sensing system

The six-component force-moment sensor K6D40 supplied by ME-Meßsysteme GmbH was mounted inside the rotating shaft and in front of the the generator bearings (see Figure C1). Apart from a thin cable connection for the power supply of the measurement amplifier and sensor, no other loads than aerodynamic and inertia loads were measured by the sensor. The miniature measurement amplifier GSV6-BT (ME-Meßsysteme GmbH) has been placed inside the rotating hub and was connected to the force-moment sensor, while sending the acquired measurement data to the main measurement computer via a wireless Bluetooth connection. The power supply cable for the rotating hub was placed inside the hollow shaft of the rotor and connected to a slip ring on the backward end of the nacelle.

The Kollmorgen brushless DC-Motor TBMS-6051 was utilised as a generator. The signals of the three inbuilt hall sensors were fed into the Kollmorgen AKD-P01206 Motor controller and in parallel into the HBM measurement amplifier.

Nacelle accelerations were measured with a TE Connectivity A3S 4030 tri-axial acceleration sensor, which was cable-connected to the HBM measurement amplifier.

The LinMot MS01-1/D magnetic position sensor was mounted on the backward end of the nacelle while the magnetic band was placed on the steel frame of the tower top. It was used for a closed loop control of the linear motor as well as the position measurement via the HBM measurement amplifier. The magnetic linear motor LinMot PS01-37x120 was used as actuator to apply the surge motion of the nacelle. A feedback control with the position sensor was realised with the LinMot C1100-GP




Figure C2. Illustration of the processing steps for rotor torque measurement from load sensor measurements.

motor driver.

Due to the limited data rate, the sampling frequency of the wireless measurement amplifier was limited to 600 Hz. A low pass filter (IIR) with an edge frequency of 200 Hz was applied to the measurement signal before transmitting it. Torque measurements were additionally filtered as described in section 5.

For hall sensors, position sensor and acceleration sensor, a sampling frequency of approximately 10 kHz was chosen.

C2 Processing steps for rotor torque measurement

The calculation procedure of the aerodynamic torque is illustrated in Figure C2. In the procedure, the rotational speed signal is phase averaged over at least 15 periods and then low pass filtered with an edge frequency of 2.5 times the motion frequency. Then, a central differencing scheme is applied to calculate the numerical derivative and the result is fed into equation (12). The measured rotor torque is also phase averaged and filtered in the same way. Finally, the aerodynamic rotor torque is calculated from equation (12). In Figure 7, the measured, phase averaged and filtered rotational speed variations as well as the compensated rotor torque are shown for all load cases. Due to the low amplitude of the rotational speed oscillation, the signal is largely scattered. However, the phase averaged results follow a sinusoidal trend in every case. Small disturbances of the gradient are disregarded using the low pass filtering.

C3 Reconstruction of rotational speed

The rotational speed signal was reconstructed from the signals of three inbuilt, equidistant hall sensors inside the motor. The sensors deliver a rising edge in the signal, when an electrical pole of the motor crosses it. Due to the presence of 6 pole pairs, 6 rising edges can be detected during one rotation in one sensor signal. The rotational speed can therefore be calculated from the fact that a rising edge occurs every 60° of rotation and the time elapsed between two rising edges. As the

signal takes approximately two times steps to rise at the sampling rate of 10 kHz, the point in time, when the signal starts to rise is detected via linear interpolation between the samples. As a consequence, the resolution of the rising edge detection can be considered as about 10 times higher than the sampling resolution.

930 **C4 Determination of the mass moment of inertia of the rotor**

The mass moment of inertia of the rotor and hub geometry was determined experimentally. When rotor torque and rotational acceleration is known while no aerodynamic load is applied, the mass moment of inertia can be calculated by the following equation.

$$J = -\frac{Q_{meas}(t)}{\frac{d\Omega}{dt}}. \quad (C1)$$

935 The rotor was accelerated with a constant torque from 0 to 300 RPM. A linear fit of the approximately linear rotor speed increase between 200 and 300 RPM was computed. The steepness gave the average angular acceleration during this process. Concurrently, the measured rotor torque, which was approximately constant, was averaged over the same period of time. Finally, the mass moment of inertia was computed by the average of 4 repetitions of this procedure and the above equation. In order to validate the result, the same procedure was repeated with a higher and a lower level of torque yielding a faster and a
940 slower acceleration of the rotor. A maximum deviation of 1.4 % between the results was reported.

Appendix D: Sources of random and systematic uncertainty

The rotor torque amplitude consists of the direct torque measurement and the inertia compensation procedure. Major sources of random and systematic uncertainty of the relevant quantities for the measurement of the rotor torque amplitude are listed below.

945 *Uncertainty of the direct torque measurement*

On the torque axis, the force-moment sensor has an uncertainty of 0.008 N m (with a confidence level of 95 %), which corresponds to below 1 % of the rated rotor torque. As the sensor is mounted with a fit into the rotor shaft, inaccuracies caused by the mounting position and angle can be considered as negligible. A few very thin wires for power transmission connect the measuring side of the sensor to the generator side. A change of the parasitic moment induced by the wires during one
950 measurement cycle may result in a minimal contribution to the random uncertainty.

Uncertainty of rotor speed measurement

Sources of random uncertainty in the rotor speed measurement are any geometrical inaccuracies of the placement of the motor poles and hall sensors as well as the rise characteristics of the hall sensors. These uncertainties do not result in systematic errors, because the influence of these parameters on the rotor speed measurement will be the same in any rotation cycle. A
955 systematic influence on the phase averaged rotor speed amplitude would therefore require the rotor rotation and surge motion to be phase locked, which is not the case.

The measurement of the time between two rising edges due to the sampling is the most crucial contributor to the random uncertainty (see dots in Figure 7). As this time is in the magnitude of $\frac{1}{105Hz}$, and can be detected with a resolution of approximately $\frac{1}{10*10kHz}$, an error of approximately 0.1 % for every measurement point can be expected. Due to the fact that
960 the measured peak-to-peak rotor speed oscillations range from 0.2 to 0.6 % of the rated rotor speed, this is quite significant. However, it can be assumed that this error is of purely random nature and is therefore drastically reduced due to the phase averaging.

A systematic influence on the rotor speed amplitude measurement is that the actual rotor speed is averaged over 1/6 of a rotation. This results in the fact that magnitudes of maxima and minima are slightly underpredicted, because the rotor speed
965 is averaged over a phase range of 60°. For the highest motion frequency, this effect yields a systematic underprediction of the rotor speed amplitude of approximately 2 %.

Uncertainty from synchronisation of rotor speed and torque measurement

Rotor speed and direct torque measurements were acquired with two different measurement amplifiers. A synchronisation was achieved by a comparison of the rotor load in wind direction (including inertia) and the nacelle acceleration. Both signals were
970 time-shifted so that the onset of the motion occurs at the same time in both signals. The accuracy of this procedure is difficult to evaluate, but is assumed to be maximum 2 % of the motion period. This results in a maximum phase shift of 7° between rotor speed and direct torque measurements. As the contribution of the direct torque measurements to the rotor torque amplitude is below 20 %, the influence of this phase shift is assumed to be comparatively small.

Uncertainty of the determination of the mass moment of inertia

The two sources of uncertainty are the rotor speed and the rotor torque measurement (both discussed above). In both, no
975 significant systematic uncertainty is expected. As the measurements are repeated only 4 times, the above described sources of random uncertainty did not completely average out. The procedure resulted in a maximum deviation of 1.4 % between the results for three independent runs with different rotor accelerations.

Uncertainty of position and velocity amplitude measurement

980 For the reproduction of the measurements with numerical model, the measurement of the actual motion amplitude is as crucial as the torque measurement itself. The positioning sensor has an overall uncertainty of 0.01 mm. This is about 0.2 % of the lowest motion amplitude. However, the most crucial uncertainty comes from the deviation of the actual motion trajectory between different motion cycles. Deviations of about 3 % have been observed when considering approximately 15 motion cycles. These deviations have been accepted and no detailed analysis on the consequences of these was performed.

985

Finally, a theoretical investigation of the combined systematic and random uncertainty of the rotor torque, surge motion and data processing with a sufficient level of detail was found to be very complex and prone to errors. However, an experimental investigation of these uncertainties would have required the construction of an elaborate calibration rig. This was out of scope of the current work. Therefore, the authors had to rely on the above theoretical analysis, where systematic errors are shown
990 to be generally in a low single-digit percentage range. In addition, a hint that the random uncertainty is also within a low single-digit percentage can be concluded from the comparison of the shown repetition results.

Appendix E: Thrust force amplitudes of the simulation study of the TUHH model rotor




Figure E1. Aerodynamic rotor thrust amplitudes of the model rotor from simulations as response to the extended surge motions plotted over motion period and rotor reduced frequency. Thrust amplitudes are normalised to the case with the highest motion period.

Appendix F: Torque amplitudes of the simulation study of the UNAFLOW and the IEA 15 MW rotor




Figure F1. Aerodynamic rotor torque amplitudes of the UNAFLOW rotor from simulations as response to surge motions plotted over motion period and rotor reduced frequency. Torque amplitudes are normalised to the case with the highest motion period.




Figure F2. Aerodynamic rotor torque amplitudes of the IEA 15 MW as a response to surge motions, plotted over motion period and rotor reduced frequency. Torque amplitudes are normalised to the scenario with the highest motion period in case of the panel method and to the quasi-steady simulation in case of the BEMT.

995 *Author contributions.* CWS planned, designed and conducted the experiment, which includes the turbine design and data processing. In addition, CWS developed the load case sets, performed the FVW simulations, led the analysis of numerical and experimental results and wrote the manuscript. UÖ performed OpenFAST simulations, supported the analysis of the simulations and reviewed the manuscript. SN implemented the extension of *panMARE* for wind turbines, supported the FVW simulations, contributed to the analysis of their results and reviewed the manuscript. PWC contributed to the theoretical discussions, supervised the works of UÖ and acquired funding. MM contributed to the theoretical discussions, supervised all works of CWS and SN, reviewed the manuscript and acquired funding.

1000 *Competing interests.* The authors declare no competing interests.

Acknowledgements. The authors kindly thank the German Federal Ministry for Economic Affairs and Climate Action (BMWK) for funding the HyStOH project (03SX409A-F) and the VAMOS project (03EE2004A-C). Special thanks go to our partners CRUSE Offshore GmbH, aerodyn engineering GmbH, JÖRSS-BLUNCK-ORDEMANN GmbH, DNV-GL and the Institute for Ship Structural Design and Analysis at the Hamburg University of Technology for the excellent cooperation in the HyStOH project as well as the partners from the VAMOS consortium, BW IDEOL, Ecole Centrale de Nantes, sowento GmbH, UL International GmbH, and DNV GL. The authors greatly appreciate the work of Klaus Wieczorek to support the experimental investigations.

1005 Publishing fees supported by Funding Programme Open Access Publishing of Hamburg University of Technology (TUHH).

[The authors kindly thank Roger Bergua, Emmanuel Branlard, Jason Jonkman and Amy Robertson \(NREL, National Renewable Energy Laboratory\) for supporting the analysis of the OpenFAST simulations.](#)

1010

References

- Bauer, M. and Abdel-Maksoud, M.: A 3-D Potential Based Boundary Element Method for Modelling and Simulation of Marine Propeller Flows, in: *IFAC Proceedings Volumes*, vol. 45 of *7th Vienna International Conference on Mathematical Modelling*, pp. 1179–1184, <https://doi.org/10.3182/20120215-3-AT-3016.00209>, 2012.
- 1015 Bayati, I., Belloli, M., Bernini, L., and Zasso, A.: Wind tunnel validation of AeroDyn within LIFES50+ project: imposed Surge and Pitch tests, *J Phys: Conf Ser*, 753, 092 001, <https://doi.org/10.1088/1742-6596/753/9/092001>, 2016.
- Bayati, I., Belloli, M., Bernini, L., Boldrin, D., Boorsma, K., Caboni, M., Cormier, M., Mikkelsen, R., Lutz, T., and Zasso, A.: UN-AFLOW project: UNsteady Aerodynamics of FLOating Wind turbines, *J Phys: Conf Ser*, 1037, 072 037, <https://doi.org/10.1088/1742-6596/1037/7/072037>, 2018.
- 1020 Bergua, R., Robertson, A., Jonkman, J., Branlard, E., Fontanella, A., Belloli, M., Schito, P., Zasso, A., Persico, G., Sanvito, A., Amet, E., Brun, C., Campaña-Alonso, G., Martín-San-Román, R., Cai, R., Cai, J., Qian, Q., Maoshi, W., Beardsell, A., Pirrung, G., Ramos-García, N., Shi, W., Fu, J., Corniglioni, R., Lovera, A., Galván, J., Nygaard, T. A., dos Santos, C. R., Gilbert, P., Joulin, P.-A., Blondel, F., Frickel, E., Chen, P., Hu, Z., Boisard, R., Yilmazlar, K., Croce, A., Harnois, V., Zhang, L., Li, Y., Aristondo, A., Mendikoa Alonso, I., Mancini, S., Boorsma, K., Savenije, F., Marten, D., Soto-Valle, R., Schulz, C. W., Netzband, S., Bianchini, A., Papi, F., Cioni, S., Trubat, P., Alarcon, D., Molins, C., Cormier, M., Brüker, K., Lutz, T., Xiao, Q., Deng, Z., Haudin, F., and Goveas, A.: OC6 project Phase III: validation of the aerodynamic loading on a wind turbine rotor undergoing large motion caused by a floating support structure, *Wind Energy Sci*, 8, 465–485, <https://doi.org/10.5194/wes-8-465-2023>, 2023.
- Branlard, E., Jonkman, B., Pirrung, G. R., Dixon, K., and Jonkman, J.: Dynamic inflow and unsteady aerodynamics models for modal and stability analyses in OpenFAST, *J Phys: Conf Ser*, 2265, 032 044, <https://doi.org/10.1088/1742-6596/2265/3/032044>, 2022.
- 1030 Chen, Z., Wang, X., and Kang, S.: Effect of the Coupled Pitch–Yaw Motion on the Unsteady Aerodynamic Performance and Structural Response of a Floating Offshore Wind Turbine, *Processes*, 9, 290, <https://doi.org/10.3390/pr9020290>, 2021.
- Cormier, M., Caboni, M., Lutz, T., Boorsma, K., and Krämer, E.: Numerical analysis of unsteady aerodynamics of floating offshore wind turbines, *J Phys: Conf Ser*, 1037, 072 048, <https://doi.org/10.1088/1742-6596/1037/7/072048>, 2018.
- Damiani, R. R. and Hayman, G.: The Unsteady Aerodynamics Module For FAST8, Tech. Rep. NREL/TP–5000-66347, 1576488, National Renewable Energy Lab. (NREL), Golden, CO (United States), <https://doi.org/10.2172/1576488>, 2019.
- 1035 de Vaal, J., Hansen, M. L., and Moan, T.: Effect of wind turbine surge motion on rotor thrust and induced velocity, *Wind Energ*, 17, 105–121, <https://doi.org/10.1002/we.1562>, 2014.
- Drela, M.: XFOIL: An Analysis and Design System for Low Reynolds Number Airfoils, in: *Low Reynolds Number Aerodynamics*, edited by Mueller, T. J., *Lecture Notes in Engineering*, pp. 1–12, Springer, https://doi.org/10.1007/978-3-642-84010-4_1, 1989.
- 1040 Eliassen, L.: Aerodynamic loads on a wind turbine rotor in axial motion, phdthesis, University of Stavanger, <http://hdl.handle.net/11250/284344>, 2015.
- Fang, Y., Duan, L., Han, Z., Zhao, Y., and Yang, H.: Numerical analysis of aerodynamic performance of a floating offshore wind turbine under pitch motion, *Energy*, 192, 116 621, <https://doi.org/10.1016/j.energy.2019.116621>, 2020.
- Farrugia, R., Sant, T., and Micallef, D.: Investigating the aerodynamic performance of a model offshore floating wind turbine, *Renew Energ*, 70, 24–30, <https://doi.org/10.1016/j.renene.2013.12.043>, 2014.
- 1045 Farrugia, R., Sant, T., and Micallef, D.: A study on the aerodynamics of a floating wind turbine rotor, *Renew Energ*, 86, 770–784, <https://doi.org/10.1016/j.renene.2015.08.063>, 2015.

- Ferreira, C., Yu, W., Sala, A., and Viré, A.: Dynamic inflow model for a floating horizontal axis wind turbine in surge motion, *Wind Energy Sci*, 7, 469–485, <https://doi.org/10.5194/wes-7-469-2022>, 2022.
- 1050 Fontanella, A., Bayati, I., Mikkelsen, R., Belloli, M., and Zasso, A.: UNAFLOW: a holistic wind tunnel experiment about the aerodynamic response of floating wind turbines under imposed surge motion, *Wind Energy Sci*, 6, 1169–1190, <https://doi.org/10.5194/wes-6-1169-2021>, 2021.
- Fontanella, A., Facchinetti, A., Di Carlo, S., and Belloli, M.: Wind tunnel investigation of the aerodynamic response of two 15 MW floating wind turbines, *Wind Energy Sci*, 7, 1711–1729, <https://doi.org/10.5194/wes-7-1711-2022>, 2022.
- 1055 Fontanella, A., Daka, E., Novais, F., and Belloli, M.: Aerodynamic response of a floating wind turbine scale model with inclusion of reference control functionalities, <https://doi.org/10.5194/wes-2023-29>, preprint, 2023.
- Gaertner, E., Rinker, J., Sethuraman, L., Zahle, F., Anderson, B., Barter, G. E., Abbas, N. J., Meng, F., Bortolotti, P., Skrzypinski, W., Scott, G. N., Feil, R., Bredmose, H., Dykes, K., Shields, M., Allen, C., and Viselli, A.: IEA Wind TCP Task 37: Definition of the IEA 15-Megawatt Offshore Reference Wind Turbine, Tech. Rep. NREL/TP-5000-75698, National Renewable Energy Lab. (NREL), Golden, CO
- 1060 (United States), <https://doi.org/10.2172/1603478>, 2020.
- Jonkman, J.: OpenFAST/openfast: OpenFAST v3.1.0, <https://doi.org/10.5281/zenodo.6324288>, 2022.
- Jonkman, J., Butterfield, S., Musial, W., and Scott, G.: Definition of a 5-MW Reference Wind Turbine for Offshore System Development, Tech. Rep. NREL/TP-500-38060, National Renewable Energy Lab. (NREL), Golden, CO (United States), <https://doi.org/10.2172/947422>, 2009.
- 1065 Leishman, J. G.: Principles of Helicopter Aerodynamics, Cambridge University Press, 1st edn., 2000.
- Leishman, J. G.: Challenges in modelling the unsteady aerodynamics of wind turbines, *Wind Energy*, 5, 85–132, <https://doi.org/10.1002/we.62>, 2002.
- Leishman, J. G. and Beddoes, T. S.: A Semi-Empirical Model for Dynamic Stall, *J Am Helicopter Soc*, 34, 3–17, <https://doi.org/https://doi.org/10.4050/JAHS.34.3.3>, 1989.
- 1070 Lienard, C., Boisard, R., and Daudin, C.: Aerodynamic Behavior of a Floating Offshore Wind Turbine, *AIAA Journal*, 58, 3835–3847, <https://doi.org/10.2514/1.J059255>, 2020.
- Loewy, R. G.: A Two-Dimensional Approximation to the Unsteady Aerodynamics of Rotary Wings, *J Aeronaut Sci*, 24, 81–92, <https://doi.org/10.2514/8.3777>, 1957.
- Lyon, C. A., Broeren, A. P., Giguere, P., Gopalarathnam, A., and Selig, M. S.: Summary of Low-Speed Airfoil Data, Volume 3, Tech. rep., University of Illinois, ISBN: 0-9646747-3-4, SoarTech Publications, 1997.
- 1075 Mancini, S., Boorsma, K., Caboni, M., Cormier, M., Lutz, T., Schito, P., and Zasso, A.: Characterization of the unsteady aerodynamic response of a floating offshore wind turbine to surge motion, *Wind Energy Sci*, 5, 1713–1730, <https://doi.org/10.5194/wes-5-1713-2020>, 2020.
- Mancini, S., Boorsma, K., Caboni, M., Hermans, K., and Savenije, F.: An engineering modification to the blade element momentum method for floating wind turbines, *J Phys: Conf Ser*, 2265, 042 017, <https://doi.org/10.1088/1742-6596/2265/4/042017>, 2022.
- 1080 Meng, H., Su, H., Guo, J., Qu, T., and Lei, L.: Experimental investigation on the power and thrust characteristics of a wind turbine model subjected to surge and sway motions, *Renew Energ*, 181, 1325–1337, <https://doi.org/10.1016/j.renene.2021.10.003>, 2022.
- Micallef, D. and Sant, T.: Loading effects on floating offshore horizontal axis wind turbines in surge motion, *Renew Energ*, 83, 737–748, <https://doi.org/10.1016/j.renene.2015.05.016>, 2015.

- 1085 Moriarty, P. J. and Hansen, A. C.: AeroDyn Theory Manual, Tech. Rep. NREL/TP-500-36881, National Renewable Energy Lab., Golden, CO (US), <https://doi.org/10.2172/15014831>, 2005.
- Netzband, S., Schulz, C. W., Götttsche, U., Ferreira González, D., and Abdel-Maksoud, M.: A panel method for floating offshore wind turbine simulations with fully integrated aero- and hydrodynamic modelling in time domain, *Ship Technol Res*, 65, 123–136, <https://doi.org/10.1080/09377255.2018.1475710>, 2018.
- 1090 Netzband, S., Schulz, C. W., and Abdel-Maksoud, M.: Self-aligning behaviour of a passively yawing floating offshore wind turbine, *Ship Technol Res*, 67, 15–25, <https://doi.org/10.1080/09377255.2018.1555986>, 2020.
- Netzband, S., Schulz, C. W., Özinan, U., Adam, R., Choynet, T., Cheng, P. W., and Abdel-Maksoud, M.: Validation of a panel method with full-scale FOWT measurements and verification with engineering models, *J Phys: Conf Ser*, under review, 2023.
- Ribeiro, A. F. P., Casalino, D., and Ferreira, C. S.: Nonlinear inviscid aerodynamics of a wind turbine rotor in surge, sway, and yaw motions using a free-wake panel method, *Wind Energ Sci*, 8, 661–675, <https://doi.org/10.5194/wes-8-661-2023>, 2023.
- 1095 Roura, M., Cuerva, A., Sanz-Andrés, A., and Barrero-Gil, A.: A panel method free-wake code for aeroelastic rotor predictions, *Wind Energ*, 13, 357–371, <https://doi.org/10.1002/we.358>, 2010.
- Sant, T. and Cuschieri, K.: Comparing Three Aerodynamic Models for Predicting the Thrust and Power Characteristics of a Yawed Floating Wind Turbine Rotor, *J Sol Energy Eng*, 138, 031 004, <https://doi.org/10.1115/1.4032684>, 2016.
- 1100 Sant, T., Bonnici, D., Farrugia, R., and Micallef, D.: Measurements and modelling of the power performance of a model floating wind turbine under controlled conditions, *Wind Energ*, 18, 811–834, <https://doi.org/10.1002/we.1730>, 2015.
- Schepers, J. G.: Engineering models in wind energy aerodynamics: development, implementation and analysis using dedicated aerodynamic measurements., phdthesis, Delft University of Technology, iSBN: 9789461915078, 2012.
- Schulz, C. W., Wang, K., Wiczorek, K., Netzband, S., and Abdel-Maksoud, M.: Experimental and numerical investigation of the yaw moment of a downwind coned wind turbine rotor, *Wind Energ*, 25, 1995–2015, <https://doi.org/10.1002/we.2779>, 2022.
- Schulz, C. W., Özinan, U., Netzband, S., Cheng, P. W., and Abdel-Maksoud, M.: The Impact of Unsteadiness on the Aerodynamic Loads of a Floating Offshore Wind Turbine, *J Phys: Conf Ser*, under review, 2023.
- Sebastian, T. and Lackner, M.: Analysis of the Induction and Wake Evolution of an Offshore Floating Wind Turbine, *Energies*, 5, 968–1000, <https://doi.org/10.3390/en5040968>, 2012.
- 1110 Sebastian, T. and Lackner, M.: Characterization of the unsteady aerodynamics of offshore floating wind turbines, *Wind Energ*, 16, 339–352, <https://doi.org/10.1002/we.545>, 2013.
- Sivalingam, K., Martin, S., and Singapore Wala, A.: Numerical Validation of Floating Offshore Wind Turbine Scaled Rotors for Surge Motion, *Energies*, 11, 2578, <https://doi.org/10.3390/en11102578>, 2018.
- Snel, H., Schepers, J. G., van Bussel, G J W, Vermeer, L J, Rawlinson Smith, R I, Voutsinas, S, van Holten, T, Oye, S, and Bareiß, R: Joint investigation of dynamic inflow effects and implementation of an engineering method, Tech. Rep. ECN-C-94-107, Netherlands Energy Research Center, 1995.
- 1115 Tran, T. T. and Kim, D.-H.: The platform pitching motion of floating offshore wind turbine: A preliminary unsteady aerodynamic analysis, *Renew Energ*, 142, 65–81, <https://doi.org/10.1016/j.jweia.2015.03.009>, 2015.
- Tran, T. T., Kim, D.-H., and Hieu Nguyen, B.: Aerodynamic Interference Effect of Huge Wind Turbine Blades With Periodic Surge Motions Using Overset Grid-Based Computational Fluid Dynamics Approach, *J Sol Energy Eng*, 137, 061 003, <https://doi.org/10.1115/1.4031184>, 2015.
- 1120

- van Garrel, A.: Multilevel panel method for wind turbine rotor flow simulations, phdthesis, University of Twente, <https://doi.org/10.3990/1.9789036542241>, ISBN: 9789036542241, 2016.
- 1125 Wang, Y. and Abdel-Maksoud, M.: Coupling wake alignment lifting line method and boundary element method for open water and unsteady propeller simulation, *Ocean Eng*, 213, 107 738, <https://doi.org/10.1016/j.oceaneng.2020.107738>, 2020.
- Wei, N. J. and Dabiri, J. O.: Phase-averaged dynamics of a periodically surging wind turbine, *J Renew Sustain Energy*, 14, 013 305, <https://doi.org/10.1063/5.0076029>, 2022.
- Wen, B., Tian, X., Dong, X., Peng, Z., and Zhang, W.: Influences of surge motion on the power and thrust characteristics of an offshore floating wind turbine, *Energy*, 141, 2054–2068, <https://doi.org/10.1016/j.energy.2017.11.090>, 2017.
- 1130 Wu, C.-H. K. and Nguyen, V.-T.: Aerodynamic simulations of offshore floating wind turbine in platform-induced pitching motion: Numerical simulations of FOWT in coupled motions, *Wind Energ*, 20, 835–858, <https://doi.org/10.1002/we.2066>, 2017.